

Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

Complementary

System Voltage	600 V AC at 50/60 Hz
[Ie] rated operational current AC	9 A
Motor power hp	0.3 hp at 120 V AC for 1 phase motors 1 hp at 240 V AC for 1 phase motors 2 hp at 208 V AC for 3 phases motors 2 hp at 230 V AC for 3 phases motors 5 hp at 460 V AC for 3 phases motors 7.5 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	240 V AC 600 V AC
Auxiliary contact composition	1 NO + 1 NC
Location of connection	Line

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1440 - Schneider Electric declaration of conformity	Compliant - since 1440 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.