



## Main

Accessory / separate part designation	Pre-wired M23 female connector
Accessory / separate part destination	Absolute single turn parallel encoder
Accessory / separate part category	Connection accessories
Accessory / separate part type	Pre-wired connector
Cable length	32.81 ft (10 m)
Total number of wires	16
Shape of connector	Straight

## Complementary

Product weight	1.74 lb(US) (0.79 kg)
----------------	-----------------------

## Environment

## Offer Sustainability


Not Green Premium product	Not Green Premium product
Compliant - since 0701 - Schneider Electric declaration of conformity	Compliant - since 0701 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Diisononyl phthalate (DINP), which is known to the State of California to cause cancer, and	Diisononyl phthalate (DINP), which is known to the State of California to cause cancer, and
Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

## Contractual warranty

Warranty period	18 months
-----------------	-----------

## Wiring Diagram

### Pre-wired Connector Connections



(1) Direction of rotation for pin 16

Pin number	Function	Colour
1	Gnd	WH
2	V Supply	BN
3	d0	GN
4	d1	YE
5	d2	GY

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

6	d3	OG
7	d4	BU
8	d5	RD
9	d6	BK
10	d7	VT
11	d8	WH/BN
12	d9	WH/GN
13	d10	WH/YE
14	d11	WH/BK
15	d12	WH/OG
16	Direction	WH/RD