

# Sound Processor with Built-in 3-band Equalizer

## BD37532FV

### General Description

BD37532FV is a sound processor with built-in 3-band equalizer for car audio. A stereo input selector is available that functions to switch single end input and ground isolation input, input-gain control, main volume, loudness, 5ch fader volume and LPF for subwoofer. Moreover, "Advanced switch circuit", which is an original ROHM technology, can reduce various switching noise (ex. No-signal, low frequency like 20Hz & large signal inputs). Also, "Advanced switch" makes control of microcomputer easier, and constructs a high quality car audio system.

### Features

- Reduced switching noise of input gain control, mute, main volume, fader volume, bass, middle, treble, loudness by using advanced switch circuit
- Built-in differential input selector that can make various combination of single-ended / differential input.
- Built-in ground isolation amplifier inputs, which is ideal for external stereo input.
- Built-in input gain controller reduces volume switching noise for portable audio input.
- Decreased number of external components due to built-in 3-band equalizer filter, LPF for subwoofer and loudness filter. It is possible to freely control Q, Gv, fo of 3-band equalizer and fc of LPF, Gv of loudness by I<sup>2</sup>C BUS control.
- A gain adjustment quantity of ±20dB with a 1 dB step gain adjustment is possible for bass, middle and treble.
- Equipped with terminals for subwoofer outputs. Also, the audio signal outputs of the front, rear and subwoofer can be chosen using the I<sup>2</sup>C BUS control.
- Energy-saving design resulting in low current consumption is achieved utilizing the BiCMOS process. It has the advantage in quality over scaling down the power heat control of the internal regulators.
- Input pins and output pins are organized and separately laid out in such a way that it simplifies the pattern layout of the PCB and decreases the board dimensions.
- It is possible to control I<sup>2</sup>C BUS with 3.3V / 5V.

### Applications


It is optimal for car audio systems. It can also be used for audio equipments like mini Compo, micro Compo, TV etc.

### Key Specifications


|  |                |
|--|----------------|
| ■ Power Supply Voltage Range:                  | 7.0V to 9.5V   |
| ■ Circuit Current (No Signal):                 | 38mA(Typ)      |
| ■ Total Harmonic Distortion 1:<br>(FRONT,REAR) | 0.001%(Typ)    |
| ■ Total Harmonic Distortion 2:<br>(SUBWOOFER)  | 0.002%(Typ)    |
| ■ Maximum Input Voltage:                       | 2.3Vrms(Typ)   |
| ■ Crosstalk Between Selectors:                 | -100dB(Typ)    |
| ■ Volume Control Range:                        | +15dB to -79dB |
| ■ Output Noise Voltage 1:<br>(FRONT,REAR)      | 3.8μVrms(Typ)  |
| ■ Output Noise Voltage 2:<br>(SUBWOOFER)       | 4.8μVrms(Typ)  |
| ■ Residual Output Noise Voltage:               | 1.8μVrms(Typ)  |
| ■ Operating Temperature Range:                 | -40°C to +85°C |

### Package

W(Typ) x D(Typ) x H(Max)



Typical Application Circuit




About single input 1 to 3, it is possible to change from single input to GND Isolation input 2,3.

About GND Isolation1 and Full Differential, it is possible to change from differential input to single input 4 to 6.

Unit  
R : [Ω]  
C : [F]


Pin Configuration



Pin Descriptions

| Pin No. | Pin Name | Description                      | Pin No. | Pin Name | Description                                   |
|---------|----------|----------------------------------|---------|----------|---|
| 1       | A1       | A input terminal of 1ch          | 15      | MUTE     | External compulsory mute terminal             |
| 2       | A2       | A input terminal of 2ch          | 16      | TEST2    | Test pin                                      |
| 3       | B1       | B input terminal of 1ch          | 17      | TEST3    | Test pin                                      |
| 4       | B2       | B input terminal of 2ch          | 18      | OUTS2    | Subwoofer output terminal of 2ch              |
| 5       | C1       | C input terminal of 1ch          | 19      | OUTS1    | Subwoofer output terminal of 1ch              |
| 6       | C2       | C input terminal of 2ch          | 20      | OUTR2    | Rear output terminal of 2ch                   |
| 7       | DP1      | D positive input terminal of 1ch | 21      | OUTR1    | Rear output terminal of 1ch                   |
| 8       | DN       | D negative input terminal        | 22      | OUTF2    | Front output terminal of 2ch                  |
| 9       | DP2      | D positive input terminal of 2ch | 23      | OUTF1    | Front output terminal of 1ch                  |
| 10      | EP1      | E positive input terminal of 1ch | 24      | VCC      | Power supply terminal                         |
| 11      | EN1      | E negative input terminal of 1ch | 25      | SCL      | I <sup>2</sup> C Communication clock terminal |
| 12      | EN2      | E negative input terminal of 2ch | 26      | SDA      | I <sup>2</sup> C Communication data terminal  |
| 13      | EP2      | E positive input terminal of 2ch | 27      | GND      | GND terminal                                  |
| 14      | TEST1    | Test pin                         | 28      | FIL      | VCC/2 terminal                                |

Block Diagram



**Absolute Maximum Ratings (Ta=25°C)**

| Parameter            | Symbol           | Rating                          | Unit |
|----------------------|------------------|---------------------------------|------|
| Power supply Voltage | V <sub>CC</sub>  | 10.0                            | V    |
| Input voltage        | V <sub>IN</sub>  | V <sub>CC</sub> +0.3 to GND-0.3 | V    |
| Power Dissipation    | P <sub>d</sub>   | 1.06 (Note 1)                   | W    |
| Storage Temperature  | T <sub>stg</sub> | -55 to +150                     | °C   |

(Note 1) When mounted on ROHM Standard board(70x70x1.6 (mm<sup>3</sup>), derate by 8.5mW/°C for Ta=25°C or more.  
Thermal resistance θ<sub>ja</sub> = 117.6(°C/W)

Material : A FR4 glass epoxy board(3% or less of copper foil area)

**Caution:** Operating the IC over the absolute maximum ratings may damage the IC. The damage can either be a short circuit between pins or an open circuit between pins and the internal circuitry. Therefore, it is important to consider circuit protection measures, such as adding a fuse, in case the IC is operated over the absolute maximum ratings.

**Recommended Operating Conditions**

| Parameter            | Symbol           | Limit      | Unit |
|----------------------|------------------|------------|------|
| Power Supply Voltage | V <sub>CC</sub>  | 7.0 to 9.5 | V    |
| Temperature          | T <sub>opr</sub> | -40 to +85 | °C   |

**Electrical Characteristics**

(Unless otherwise noted, Ta=25°C, V<sub>CC</sub>=8.5V, f=1kHz, V<sub>IN</sub>=1Vrms, R<sub>g</sub>=600Ω, R<sub>L</sub>=10kΩ, A1 input, Input gain 0dB, Mute OFF, Volume 0dB, Tone control 0dB, Loudness 0dB, LPF OFF, Fader 0dB)

| BLOCK                                | Parameter                                | Symbol            | Limit |       |      | Unit  | Conditions  |
|--------------------------------------|--|-------------------|-------|-------|------|---|---|
|                                      |  |                   | Min   | Typ   | Max  |   |   |
| GENERAL                              | Circuit Current                          | I <sub>Q</sub>    | -     | 38    | 48   | mA  | No signal   |
|                                      | Voltage Gain                             | G <sub>V</sub>    | -1.5  | 0     | +1.5 | dB  | G <sub>V</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )                             |
|                                      | Channel Balance                          | CB                | -1.5  | 0     | +1.5 | dB  | CB = G <sub>V1</sub> -G <sub>V2</sub>   |
|                                      | Total Harmonic Distortion 1 (FRONT,REAR) | THD+N1            | -     | 0.001 | 0.05 | %   | V <sub>OUT</sub> =1Vrms<br>BW=400Hz-30KHz   |
|                                      | Total Harmonic Distortion 2 (SUBWOOFER)  | THD+N2            | -     | 0.002 | 0.05 | %   | V <sub>OUT</sub> =1Vrms<br>BW=400Hz-30KHz   |
|                                      | Output Noise Voltage 1 (FRONT,REAR) *    | V <sub>NO1</sub>  | -     | 3.8   | 15   | μVrms   | R <sub>g</sub> = 0Ω<br>BW = IHF-A   |
|                                      | Output Noise Voltage 2 (SUBWOOFER) *     | V <sub>NO2</sub>  | -     | 4.8   | 15   | μVrms   | R <sub>g</sub> = 0Ω<br>BW = IHF-A   |
|                                      | Residual Output Noise Voltage *          | V <sub>NOR</sub>  | -     | 1.8   | 10   | μVrms   | Fader = -∞dB<br>R <sub>g</sub> = 0Ω<br>BW = IHF-A                                     |
|                                      | Crosstalk Between Channels*              | CTC               | -     | -100  | -90  | dB  | R <sub>g</sub> = 0Ω<br>CTC=20log(V <sub>OUT</sub> /V <sub>IN</sub> )<br>BW = IHF-A    |
| INPUT SELECTOR                       | Ripple Rejection                         | RR                | -     | -70   | -40  | dB  | f=1kHz<br>V <sub>RR</sub> =100mVrms<br>RR=20log(V <sub>CC</sub> IN/V <sub>OUT</sub> ) |
|                                      | Input Impedance (A, B, C)                | R <sub>IN_S</sub> | 70    | 100   | 130  | kΩ  |   |
|                                      | Input Impedance (D, E)                   | R <sub>IN_D</sub> | 175   | 250   | 325  | kΩ  |   |
|                                      | Maximum Input Voltage                    | V <sub>IM</sub>   | 2.1   | 2.3   | -    | Vrms  | V <sub>IM</sub> at THD+N(V <sub>OUT</sub> )=1 %<br>BW=400Hz-30KHz                     |
|                                      | Crosstalk Between Selectors *            | CTS               | -     | -100  | -90  | dB  | R <sub>g</sub> = 0Ω<br>CTS=20log(V <sub>OUT</sub> /V <sub>IN</sub> )<br>BW = IHF-A    |
| Common Mode Rejection Ratio * (D, E) | CMRR                                     | 50                | 65    | -     | dB   | XP1 and XN input<br>XP2 and XN input<br>CMRR=20log(V <sub>IN</sub> /V <sub>OUT</sub> )<br>BW = IHF-A,[*X · · · D,E] |   |

Electrical Characteristics – continued

| BLOCK                  | Parameter               | Symbol              | Limit |      |      | Unit                       | Conditions  |
|------------------------|-------------------------|---------------------|-------|------|------|----------------------------|---|
|                        |                         |                     | Min   | Typ  | Max  |                            |   |
| INPUT GAIN             | Minimum Input Gain      | G <sub>IN_MIN</sub> | -2    | 0    | +2   | dB                         | Input gain 0dB<br>V <sub>IN</sub> =100mVrms<br>G <sub>IN</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )     |
|                        | Maximum Input Gain      | G <sub>IN_MAX</sub> | +18   | +20  | +22  | dB                         | Input Gain +20dB<br>V <sub>IN</sub> =100mVrms<br>G <sub>IN</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )   |
|                        | Gain Set Error          | G <sub>IN_ERR</sub> | -2    | 0    | +2   | dB                         | Gain=+20dB to +1dB  |
| MUTE                   | Mute Attenuation *      | G <sub>MUTE</sub>   | -     | -105 | -85  | dB                         | Mute ON<br>G <sub>MUTE</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )<br>BW = IHF-A                         |
| VOLUME                 | Maximum Gain            | G <sub>V_MAX</sub>  | 13    | 15   | 17   | dB                         | Volume = 15dB<br>V <sub>IN</sub> =100mVrms<br>G <sub>V</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )       |
|                        | Maximum Attenuation *   | G <sub>V_MIN</sub>  | -     | -100 | -85  | dB                         | Volume = -∞dB<br>G <sub>V</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )<br>BW = IHF-A                      |
|                        | Attenuation Set Error 1 | G <sub>V_ERR1</sub> | -2    | 0    | +2   | dB                         | GAIN & ATT=+15dB to -15dB   |
|                        | Attenuation Set Error 2 | G <sub>V_ERR2</sub> | -3    | 0    | +3   | dB                         | ATT=-16dB to -47dB  |
|                        | Attenuation Set Error 3 | G <sub>V_ERR3</sub> | -4    | 0    | +4   | dB                         | ATT=-48dB to -79dB  |
| BASS                   | Maximum Boost Gain      | G <sub>B_BST</sub>  | 18    | 20   | 22   | dB                         | Gain=+20dB f=100Hz<br>V <sub>IN</sub> =100mVrms<br>G <sub>B</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> ) |
|                        | Maximum Cut Gain        | G <sub>B_CUT</sub>  | -22   | -20  | -18  | dB                         | Gain=-20dB f=100Hz<br>V <sub>IN</sub> =2Vrms<br>G <sub>B</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> )    |
|                        | Gain Set Error          | G <sub>B_ERR</sub>  | -2    | 0    | +2   | dB                         | Gain=+20dB to -20dB<br>f=100Hz  |
| MIDDLE                 | Maximum Boost Gain      | G <sub>M_BST</sub>  | 18    | 20   | 22   | dB                         | Gain=+20dB f=1KHz<br>V <sub>IN</sub> =100mVrms<br>G <sub>M</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> )  |
|                        | Maximum Cut Gain        | G <sub>M_CUT</sub>  | -22   | -20  | -18  | dB                         | Gain=-20dB f=1kHz<br>V <sub>IN</sub> =2Vrms<br>G <sub>M</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> )     |
|                        | Gain Set Error          | G <sub>M_ERR</sub>  | -2    | 0    | +2   | dB                         | Gain=+20dB to -20dB f=1kHz  |
| TREBLE                 | Maximum Boost Gain      | G <sub>T_BST</sub>  | 18    | 20   | 22   | dB                         | Gain=+20dB f=10kHz<br>V <sub>IN</sub> =100mVrms<br>G <sub>T</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> ) |
|                        | Maximum Cut Gain        | G <sub>T_CUT</sub>  | -22   | -20  | -18  | dB                         | Gain=-20dB f=10kHz<br>V <sub>IN</sub> =2Vrms<br>G <sub>T</sub> =20log (V <sub>OUT</sub> /V <sub>IN</sub> )    |
|                        | Gain Set Error          | G <sub>T_ERR</sub>  | -2    | 0    | +2   | dB                         | Gain=+20dB to -20dB<br>f=10kHz  |
| FADER / SUBWOOFER      | Maximum Boost Gain      | G <sub>F_BST</sub>  | 13    | 15   | 17   | dB                         | Fader=15dB<br>V <sub>IN</sub> =100mVrms<br>G <sub>F</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )          |
|                        | Maximum Attenuation *   | G <sub>F_MIN</sub>  | -     | -100 | -90  | dB                         | Fader = -∞dB<br>G <sub>F</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )<br>BW = IHF-A                       |
|                        | Gain Set Error          | G <sub>F_ERR</sub>  | -2    | 0    | +2   | dB                         | Gain=+15dB to +1dB  |
|                        | Attenuation Set Error 1 | G <sub>F_ERR1</sub> | -2    | 0    | +2   | dB                         | ATT=-1dB to -15dB   |
|                        | Attenuation Set Error 2 | G <sub>F_ERR2</sub> | -3    | 0    | +3   | dB                         | ATT=-16dB to -47dB  |
|                        | Attenuation Set Error 3 | G <sub>F_ERR3</sub> | -4    | 0    | +4   | dB                         | ATT=-48dB to -79dB  |
|                        | Output Impedance        | R <sub>OUT</sub>    | -     | -    | 50   | Ω                          | V <sub>IN</sub> =100mVrms   |
| Maximum Output Voltage | V <sub>OM</sub>         | 2                   | 2.2   | -    | Vrms | THD+N=1%<br>BW=400Hz-30KHz |   |
| LOUDNESS               | Maximum Gain            | G <sub>L_MAX</sub>  | 17    | 20   | 23   | dB                         | Gain 20dB<br>V <sub>IN</sub> =100mVrms<br>G <sub>L</sub> =20log(V <sub>OUT</sub> /V <sub>IN</sub> )           |
|                        | Gain Set Error          | G <sub>L_ERR</sub>  | -2    | 0    | +2   | dB                         | GAIN=+20dB to +1dB  |

VP-9690A (Average value detection, effective value display) filter by Matsushita Communication is used for \* measurement.  
Phase between input / output is same.

Typical Performance Curves




Figure 1. Circuit Current (No Signal) vs Power Supply Voltage




Figure 2. Total Harmonic Distortion vs Output Voltage




Figure 3. Gain vs Frequency




Figure 4. Bass Gain vs Frequency

Typical Performance Curves – continued




Figure 5. Bass fo vs Frequency




Figure 6. Bass Q vs Frequency




Figure 7. Middle Gain vs Frequency




Figure 8. Middle fo vs Frequency

Typical Performance Curves – continued




Figure 9. Middle Q vs Frequency




Figure 10. Treble Gain vs Frequency




Figure 11. Treble fo vs Frequency




Figure 12. Treble Q vs Frequency



Typical Performance Curves – continued




Figure 13. Output Noise vs Volume Gain




Figure 14. Output Noise vs Bass Gain




Figure 15. Output Noise vs Middle Gain




Figure 16. Output Noise vs Treble Gain

Typical Performance Curves – continued




Figure 17. CMRR vs Frequency




Figure 18. Output Voltage vs R<sub>LOAD</sub>




Figure 19. Advanced Switch 1




Figure 20. Advanced Switch 2

Timing Chart

CONTROL SIGNAL SPECIFICATION

(1) Electrical Specifications and Timing for Bus Lines and I/O Stages




Figure 21. Definition of Timing on the I²C-bus

Table 1 Characteristics of the SDA and SCL bus lines for I²C-bus devices  
(Unless specified particularly, Ta=25°C, Vcc=8.5V)

| Parameter   | Symbol              | Fast-mode I²C-bus      |     | Unit |
|---|---------------------|------------------------|-----|------|
|   |                     | Min                    | Max |      |
| 1 SCL clock frequency   | f <sub>SCL</sub>    | 0                      | 400 | kHz  |
| 2 Bus free time between a STOP and START condition  | t <sub>BUF</sub>    | 1.3                    | -   | µS   |
| 3 Hold time (repeated) START condition. After this period, the first clock pulse is generated | t <sub>HD:STA</sub> | 0.6                    | -   | µS   |
| 4 LOW period of the SCL clock   | t <sub>LOW</sub>    | 1.3                    | -   | µS   |
| 5 HIGH period of the SCL clock  | t <sub>HIGH</sub>   | 0.6                    | -   | µS   |
| 6 Set-up time for a repeated START condition  | t <sub>SU:STA</sub> | 0.6                    | -   | µS   |
| 7 Data hold time:   | t <sub>HD:DAT</sub> | 0.06 <sup>(Note)</sup> | -   | µS   |
| 8 Data set-up time  | t <sub>SU:DAT</sub> | 120                    | -   | ns   |
| 9 Set-up time for STOP condition  | t <sub>SU:STO</sub> | 0.6                    | -   | µS   |

All values referred to VIH Min and VIL Max Levels (see Table 2).

(Note) The device must internally provide a hold time of at least 300 ns for the SDA signal (referred to the VIH Min of the SCL signal) in order to bridge the undefined region of the falling edge of SCL.

About 7 (t<sub>HD:DAT</sub>), 8(t<sub>SU:DAT</sub>), make the setup in which the margin is fully in .

Table 2 Characteristics of the SDA and SCL I/O stages for I²C-bus devices

| Parameter  | Symbol           | Fast-mode devices |     | Unit |
|--|------------------|-------------------|-----|------|
|  |                  | Min               | Max |      |
| 10 LOW level input voltage:  | V <sub>IL</sub>  | -0.3              | +1  | V    |
| 11 HIGH level input voltage:   | V <sub>IH</sub>  | 2.3               | 5   | V    |
| 12 Pulse width of spikes which must be suppressed by the input filter.     | t <sub>SP</sub>  | 0                 | 50  | ns   |
| 13 LOW level output voltage: at 3mA sink current                           | V <sub>OL1</sub> | 0                 | 0.4 | V    |
| 14 Input current each I/O pin with an input voltage between 0.4V and 4.5V. | I <sub>I</sub>   | -10               | +10 | µA   |





Figure 22. A Command Timing Example in the I²C Data Transmission


(2) I<sup>2</sup>C BUS FORMAT




- S = Start conditions (Recognition of start bit)
- Slave Address = Recognition of slave address. 7 bits in upper order are voluntary.  
The least significant bit is "L" for write mode.
- A = ACKNOWLEDGE bit (Recognition of acknowledgement)
- Select Address = Select address for volume, bass and treble.
- Data = Data on every volume and tone.
- P = Stop condition (Recognition of stop bit)

(3) I<sup>2</sup>C BUS Interface Protocol

(a) Basic form




(b) Automatic increment (Select Address increases (+1) according to the number of data.)



- (Example) ①Data1 shall be set as data of address specified by Select Address.  
 ②Data2 shall be set as data of address specified by Select Address +1.  
 ③DataN shall be set as data of address specified by Select Address +N-1.

(c) Configuration unavailable for transmission (In this case, only Select Address1 is set.)



(Note) If any data is transmitted as Select Address 2 next to data, it is recognized as data, not as Select Address 2.

(4) Slave Address

|     |    |    |    |    |    |    |     |     |
|-----|----|----|----|----|----|----|-----|-----|
| MSB |    |    |    |    |    |    | LSB |     |
| A6  | A5 | A4 | A3 | A2 | A1 | A0 | R/W |     |
| 1   | 0  | 0  | 0  | 0  | 0  | 0  | 0   | 80H |


(5) Select Address & Data

| Items           | Select Address (hex) | Data                      |                |   |                |    |                  |                              |          |
|-----------------|----------------------|---------------------------|----------------|---|----------------|----|------------------|------------------------------|----------|
|                 |                      | MSB                       | Data           |   |                |    |                  |                              | LSB      |
|                 |                      | D7                        | D6             | D5  | D4             | D3 | D2               | D1                           | D0       |
| Initial setup 1 | 01                   | Advanced switch ON/OFF    | 0              | Advanced switch time of Input Gain/Volume Tone/Fader/Loudness |                | 0  | 1                | Advanced switch time of Mute |          |
| Initial setup 2 | 02                   | LPF Phase                 | 0              | Subwoofer Output Select                                       |                | 0  | Subwoofer LPF fc |                              |          |
| Initial setup 3 | 03                   | 0                         | 0              | 0   | Loudness fo    |    | 0                | 0                            | 1        |
| Input Selector  | 05                   | Full-diff Type            | 0              | 0   | Input selector |    |                  |                              |          |
| Input gain      | 06                   | Mute ON/OFF               | 0              | 0   | Input Gain     |    |                  |                              |          |
| Volume gain     | 20                   | Volume Gain / Attenuation |                |   |                |    |                  |                              |          |
| Fader 1ch Front | 28                   | Fader Gain / Attenuation  |                |   |                |    |                  |                              |          |
| Fader 2ch Front | 29                   | Fader Gain / Attenuation  |                |   |                |    |                  |                              |          |
| Fader 1ch Rear  | 2A                   | Fader Gain / Attenuation  |                |   |                |    |                  |                              |          |
| Fader 2ch Rear  | 2B                   | Fader Gain / Attenuation  |                |   |                |    |                  |                              |          |
| Fader Subwoofer | 2C                   | Fader Gain / Attenuation  |                |   |                |    |                  |                              |          |
| Test Mode       | 30                   | 1                         | 1              | 1   | 1              | 1  | 1                | 1                            | 1        |
| Bass setup      | 41                   | 0                         | 0              | Bass fo   |                | 0  | 0                | Bass Q                       |          |
| Middle setup    | 44                   | 0                         | 0              | Middle fo   |                | 0  | 0                | Middle Q                     |          |
| Treble setup    | 47                   | 0                         | 0              | Treble fo   |                | 0  | 0                | 0                            | Treble Q |
| Bass gain       | 51                   | Bass Boost/Cut            | 0              | 0   | Bass Gain      |    |                  |                              |          |
| Middle gain     | 54                   | Middle Boost/Cut          | 0              | 0   | Middle Gain    |    |                  |                              |          |
| Treble gain     | 57                   | Treble Boost/Cut          | 0              | 0   | Treble Gain    |    |                  |                              |          |
| Loudness Gain   | 75                   | 0                         | Loudness Hicut |   | Loudness Gain  |    |                  |                              |          |
| System Reset    | FE                   | 1                         | 0              | 0   | 0              | 0  | 0                | 0                            | 1        |

 Advanced switch

Note

1. The Advanced Switch works in the latch part while changing from one function to another..
2. Upon continuous data transfer, the Select Address rolls over because of the automatic increment function, as shown below.



3. Advanced Switch is not used for the functions of input selector and subwoofer output select etc. Please turn on MUTE when changing the settings of this side of the set.
4. When using Mute function of this IC at the time of changing input selector, please switch mute ON/OFF while waiting for advanced-mute time.

Select address 01 (hex)

| Time    | MSB Advanced switch time of Mute |    |   |    |    |    |    | LSB |  |
|---------|----------------------------------|----|---|----|----|----|----|-----|--|
|         | D7                               | D6 | D5  | D4 | D3 | D2 | D1 | D0  |  |
| 0.6msec | Advanced Switch ON/OFF           | 0  | Advanced switch time of Input gain/Volume Tone/Fader/Loudness |    | 0  | 1  | 0  | 0   |  |
| 1.0msec |                                  |    |   |    |    |    | 0  | 1   |  |
| 1.4msec |                                  |    |   |    |    |    | 1  | 0   |  |
| 3.2msec |                                  |    |   |    |    |    | 1  | 1   |  |

| Time      | MSB Advanced switch time of Input gain/Volume/Tone/Fader/Loudness |    |    |    |    |    |                              | LSB |  |
|-----------|---|----|----|----|----|----|------------------------------|-----|--|
|           | D7  | D6 | D5 | D4 | D3 | D2 | D1                           | D0  |  |
| 4.7 msec  | Advanced Switch ON/OFF  | 0  | 0  | 0  | 0  | 1  | Advanced switch Time of Mute |     |  |
| 7.1 msec  |   |    | 0  | 1  |    |    |                              |     |  |
| 11.2 msec |   |    | 1  | 0  |    |    |                              |     |  |
| 14.4 msec |   |    | 1  | 1  |    |    |                              |     |  |

| Mode | MSB Advanced switch ON/OFF |    |   |    |    |    |                              | LSB |  |
|------|----------------------------|----|---|----|----|----|------------------------------|-----|--|
|      | D7                         | D6 | D5  | D4 | D3 | D2 | D1                           | D0  |  |
| OFF  | 0                          | 0  | Advanced switch time of Input gain/Volume Tone/Fader/Loudness |    | 0  | 1  | Advanced switch Time of Mute |     |  |
| ON   | 1                          |    |   |    |    |    |                              |     |  |

Select address 02(hex)


| fc          | MSB Subwoofer LPF fc |    |                         |    |    |               |    | LSB |  |
|-------------|----------------------|----|-------------------------|----|----|---------------|----|-----|--|
|             | D7                   | D6 | D5                      | D4 | D3 | D2            | D1 | D0  |  |
| OFF         | LPF Phase            | 0  | Subwoofer Output Select |    | 0  | 0             | 0  | 0   |  |
| 55Hz        |                      |    |                         |    |    | 0             | 0  | 1   |  |
| 85Hz        |                      |    |                         |    |    | 0             | 1  | 0   |  |
| 120Hz       |                      |    |                         |    |    | 0             | 1  | 1   |  |
| 160Hz       |                      |    |                         |    |    | 1             | 0  | 0   |  |
| Prohibition |                      |    |                         |    |    | Other setting |    |     |  |

| Mode        | MSB Subwoofer Output Select |    |    |    |    |                  |    | LSB |  |
|-------------|-----------------------------|----|----|----|----|------------------|----|-----|--|
|             | D7                          | D6 | D5 | D4 | D3 | D2               | D1 | D0  |  |
| LPF         | LPF Phase                   | 0  | 0  | 0  | 0  | Subwoofer LPF fc |    |     |  |
| Front       |                             |    | 0  | 1  |    |                  |    |     |  |
| Rear        |                             |    | 1  | 0  |    |                  |    |     |  |
| Prohibition |                             |    | 1  | 1  |    |                  |    |     |  |

| Phase | MSB LPF Phase |    |                         |    |    |                  |    | LSB |  |
|-------|---------------|----|-------------------------|----|----|------------------|----|-----|--|
|       | D7            | D6 | D5                      | D4 | D3 | D2               | D1 | D0  |  |
| 0°    | 0             | 0  | Subwoofer output select |    | 0  | Subwoofer LPF fc |    |     |  |
| 180°  | 1             |    |                         |    |    |                  |    |     |  |

Select address 03(hex)

| f0          | MSB Loudness fo |    |    |    |    |    |    | LSB |  |
|-------------|-----------------|----|----|----|----|----|----|-----|--|
|             | D7              | D6 | D5 | D4 | D3 | D2 | D1 | D0  |  |
| 250Hz       | 0               | 0  | 0  | 0  | 0  | 0  | 0  | 1   |  |
| 400Hz       |                 |    |    | 0  | 1  |    |    |     |  |
| 800Hz       |                 |    |    | 1  | 0  |    |    |     |  |
| Prohibition |                 |    |    | 1  | 1  |    |    |     |  |


 : Initial condition

Select address 05(hex)


| Mode                    |       |       | Input Selector             |    |    |               |    |    |    |    |   |
|-------------------------|-------|-------|----------------------------|----|----|---------------|----|----|----|----|---|
|                         | OUTF1 | OUTF2 | D7                         | D6 | D5 | D4            | D3 | D2 | D1 | D0 |   |
| A                       | A1    | A2    | Full-diff bias type select | 0  | 0  | 0             | 0  | 0  | 0  | 0  |   |
| B                       | B1    | B2    |                            |    |    | 0             | 0  | 0  | 0  | 1  | 1 |
| C                       | C1    | C2    |                            |    |    | 0             | 0  | 0  | 1  | 0  | 0 |
| D single                | DP1   | DP2   |                            |    |    | 0             | 0  | 0  | 1  | 1  | 1 |
| E1 single               | EP1   | EN1   |                            |    |    | 0             | 1  | 0  | 1  | 0  | 0 |
| E2 single               | EN2   | EP2   |                            |    |    | 0             | 1  | 0  | 1  | 1  | 1 |
| A diff                  | A1    | B1    |                            |    |    | 0             | 1  | 1  | 1  | 1  | 1 |
| C diff                  | B2    | C2    |                            |    |    | 1             | 0  | 0  | 0  | 0  | 0 |
| D diff                  | DP1   | DP2   |                            |    |    | 0             | 0  | 1  | 1  | 1  | 0 |
| E full diff             | EP1   | EP2   |                            |    |    | 0             | 1  | 0  | 0  | 0  | 0 |
| Input SHORT Prohibition |       |       |                            |    |    | Other setting |    |    |    |    |   |

Input SHORT : The input impedance of each input terminal is lowered from 100kΩ(Typ) to 6 kΩ(Typ).  
(For quick charge of coupling capacitor)


| Mode           | Full-diff Bias Type Select |    |    |                |    |    |    |    | LSB |
|----------------|----------------------------|----|----|----------------|----|----|----|----|-----|
|                | D7                         | D6 | D5 | D4             | D3 | D2 | D1 | D0 |     |
| Negative Input | 0                          | 0  | 0  | Input Selector |    |    |    |    |     |
| Bias           | 1                          |    |    |                |    |    |    |    |     |

 : Initial condition

Negative input type  
For Ground –isolation type)



Bias type  
For differential amplifier type



Select address 06 (hex)

| Gain        | MSB            |    |    | Input Gain |    |    |    | LSB |  |
|-------------|----------------|----|----|------------|----|----|----|-----|--|
|             | D7             | D6 | D5 | D4         | D3 | D2 | D1 | D0  |  |
| 0dB         | Mute<br>ON/OFF | 0  | 0  | 0          | 0  | 0  | 0  | 0   |  |
| 1dB         |                |    |    | 0          | 0  | 0  | 0  | 1   |  |
| 2dB         |                |    |    | 0          | 0  | 0  | 1  | 0   |  |
| 3dB         |                |    |    | 0          | 0  | 0  | 1  | 1   |  |
| 4dB         |                |    |    | 0          | 0  | 1  | 0  | 0   |  |
| 5dB         |                |    |    | 0          | 0  | 1  | 0  | 1   |  |
| 6dB         |                |    |    | 0          | 0  | 1  | 1  | 0   |  |
| 7dB         |                |    |    | 0          | 0  | 1  | 1  | 1   |  |
| 8dB         |                |    |    | 0          | 1  | 0  | 0  | 0   |  |
| 9dB         |                |    |    | 0          | 1  | 0  | 0  | 1   |  |
| 10dB        |                |    |    | 0          | 1  | 0  | 1  | 0   |  |
| 11dB        |                |    |    | 0          | 1  | 0  | 1  | 1   |  |
| 12dB        |                |    |    | 0          | 1  | 1  | 0  | 0   |  |
| 13dB        |                |    |    | 0          | 1  | 1  | 0  | 1   |  |
| 14dB        |                |    |    | 0          | 1  | 1  | 1  | 0   |  |
| 15dB        |                |    |    | 0          | 1  | 1  | 1  | 1   |  |
| 16dB        |                |    |    | 1          | 0  | 0  | 0  | 0   |  |
| 17dB        |                |    |    | 1          | 0  | 0  | 0  | 1   |  |
| 18dB        |                |    |    | 1          | 0  | 0  | 1  | 0   |  |
| 19dB        |                |    |    | 1          | 0  | 0  | 1  | 1   |  |
| 20dB        | 1              | 0  | 1  | 0          | 0  |    |    |     |  |
| Prohibition |                |    |    | 1          | 1  | 0  | 1  | 1   |  |
|             |                |    |    | :          | :  | :  | :  | :   |  |
|             |                |    |    | 1          | 1  | 1  | 1  | 1   |  |

| Mode | MSB |    |    | Mute ON/OFF |    |    |    | LSB |  |
|------|-----|----|----|-------------|----|----|----|-----|--|
|      | D7  | D6 | D5 | D4          | D3 | D2 | D1 | D0  |  |
| OFF  | 0   | 0  | 0  | Input Gain  |    |    |    |     |  |
| ON   | 1   |    |    |             |    |    |    |     |  |



: Initial condition



Select address 20, 28, 29, 2A, 2B, 2C (hex)

| Gain & ATT  | MSB Vol, Fader Gain / Attenuation |    |    |    |    |    |    | LSB |  |
|-------------|-----------------------------------|----|----|----|----|----|----|-----|--|
|             | D7                                | D6 | D5 | D4 | D3 | D2 | D1 | D0  |  |
| Prohibition | 0                                 | 0  | 0  | 0  | 0  | 0  | 0  | 0   |  |
|             | 0                                 | 0  | 0  | 0  | 0  | 0  | 0  | 1   |  |
|             | :                                 | :  | :  | :  | :  | :  | :  | :   |  |
|             | 0                                 | 1  | 1  | 1  | 0  | 0  | 0  | 0   |  |
| 15dB        | 0                                 | 1  | 1  | 1  | 0  | 0  | 0  | 1   |  |
| 14dB        | 0                                 | 1  | 1  | 1  | 0  | 0  | 1  | 0   |  |
| 13dB        | 0                                 | 1  | 1  | 1  | 0  | 0  | 1  | 1   |  |
| :           | :                                 | :  | :  | :  | :  | :  | :  | :   |  |
| -77dB       | 1                                 | 1  | 0  | 0  | 1  | 1  | 0  | 1   |  |
| -78dB       | 1                                 | 1  | 0  | 0  | 1  | 1  | 1  | 0   |  |
| -79dB       | 1                                 | 1  | 0  | 0  | 1  | 1  | 1  | 1   |  |
| Prohibition | 1                                 | 1  | 0  | 1  | 0  | 0  | 0  | 0   |  |
|             | :                                 | :  | :  | :  | :  | :  | :  | :   |  |
|             | 1                                 | 1  | 1  | 1  | 1  | 1  | 1  | 0   |  |
| -∞dB        | 1                                 | 1  | 1  | 1  | 1  | 1  | 1  | 1   |  |

Select address 41(hex)

| Q factor | MSB Bass |    |         |    | Q factor |    | LSB |    |
|----------|----------|----|---------|----|----------|----|-----|----|
|          | D7       | D6 | D5      | D4 | D3       | D2 | D1  | D0 |
| 0.5      | 0        | 0  | Bass fo |    | 0        | 0  | 0   | 0  |
| 1.0      |          |    |         |    |          |    | 0   | 1  |
| 1.5      |          |    |         |    |          |    | 1   | 0  |
| 2.0      |          |    |         |    |          |    | 1   | 1  |

| fo    | MSB Bass |    |    |    | fo |    | LSB           |    |
|-------|----------|----|----|----|----|----|---------------|----|
|       | D7       | D6 | D5 | D4 | D3 | D2 | D1            | D0 |
| 60Hz  | 0        | 0  | 0  | 0  | 0  | 0  | Bass Q factor |    |
| 80Hz  |          |    | 0  | 1  |    |    |               |    |
| 100Hz |          |    | 1  | 0  |    |    |               |    |
| 120Hz |          |    | 1  | 1  |    |    |               |    |

Select address 44(hex)

| Q factor | MSB Middle |    |           |    | Q factor |    | LSB |    |
|----------|------------|----|-----------|----|----------|----|-----|----|
|          | D7         | D6 | D5        | D4 | D3       | D2 | D1  | D0 |
| 0.75     | 0          | 0  | Middle fo |    | 0        | 0  | 0   | 0  |
| 1.0      |            |    |           |    |          |    | 0   | 1  |
| 1.25     |            |    |           |    |          |    | 1   | 0  |
| 1.5      |            |    |           |    |          |    | 1   | 1  |

| fo     | MSB Middle |    |    |    | fo |    | LSB             |    |
|--------|------------|----|----|----|----|----|-----------------|----|
|        | D7         | D6 | D5 | D4 | D3 | D2 | D1              | D0 |
| 500Hz  | 0          | 0  | 0  | 0  | 0  | 0  | Middle Q factor |    |
| 1kHz   |            |    | 0  | 1  |    |    |                 |    |
| 1.5kHz |            |    | 1  | 0  |    |    |                 |    |
| 2.5kHz |            |    | 1  | 1  |    |    |                 |    |

 : Initial condition

Select address 47 (hex)


| Q factor | MSB |    | Treble    |    |    |    | Q factor |    | LSB |
|----------|-----|----|-----------|----|----|----|----------|----|-----|
|          | D7  | D6 | D5        | D4 | D3 | D2 | D1       | D0 |     |
| 0.75     | 0   | 0  | Treble fo |    | 0  | 0  | 0        | 0  |     |
| 1.25     | 0   | 0  | Treble fo |    | 0  | 0  | 0        | 1  |     |

| fo      | MSB |    | Treble |    |    |    | fo |                    | LSB |
|---------|-----|----|--------|----|----|----|----|--------------------|-----|
|         | D7  | D6 | D5     | D4 | D3 | D2 | D1 | D0                 |     |
| 7.5kHz  | 0   | 0  | 0      | 0  | 0  | 0  | 0  | Treble<br>Q factor |     |
| 10kHz   |     |    | 0      | 1  |    |    |    |                    |     |
| 12.5kHz |     |    | 1      | 0  |    |    |    |                    |     |
| 15kHz   |     |    | 1      | 1  |    |    |    |                    |     |

Select address 51, 54, 57 (hex)

| Gain        | MSB   |    | Bass/Middle/Treble Gain |    |    |    |    | LSB |
|-------------|---|----|-------------------------|----|----|----|----|-----|
|             | D7  | D6 | D5                      | D4 | D3 | D2 | D1 | D0  |
| 0dB         | Bass/<br>Middle/<br>Treble<br>Boost<br>/cut | 0  | 0                       | 0  | 0  | 0  | 0  | 0   |
| 1dB         |   |    |                         | 0  | 0  | 0  | 0  | 1   |
| 2dB         |   |    |                         | 0  | 0  | 0  | 1  | 0   |
| 3dB         |   |    |                         | 0  | 0  | 0  | 1  | 1   |
| 4dB         |   |    |                         | 0  | 0  | 1  | 0  | 0   |
| 5dB         |   |    |                         | 0  | 0  | 1  | 0  | 1   |
| 6dB         |   |    |                         | 0  | 0  | 1  | 1  | 0   |
| 7dB         |   |    |                         | 0  | 0  | 1  | 1  | 1   |
| 8dB         |   |    |                         | 0  | 1  | 0  | 0  | 0   |
| 9dB         |   |    |                         | 0  | 1  | 0  | 0  | 1   |
| 10dB        |   |    |                         | 0  | 1  | 0  | 1  | 0   |
| 11dB        |   |    |                         | 0  | 1  | 0  | 1  | 1   |
| 12dB        |   |    |                         | 0  | 1  | 1  | 0  | 0   |
| 13dB        |   |    |                         | 0  | 1  | 1  | 0  | 1   |
| 14dB        |   |    |                         | 0  | 1  | 1  | 1  | 0   |
| 15dB        |   |    |                         | 0  | 1  | 1  | 1  | 1   |
| 16dB        |   |    |                         | 1  | 0  | 0  | 0  | 0   |
| 17dB        |   |    |                         | 1  | 0  | 0  | 0  | 1   |
| 18dB        |   |    |                         | 1  | 0  | 0  | 1  | 0   |
| 19dB        |   |    |                         | 1  | 0  | 0  | 1  | 1   |
| 20dB        | 1   | 0  | 1                       | 0  | 0  |    |    |     |
| Prohibition | 1   | 0  | 1                       | 0  | 1  |    |    |     |
|             | :   | :  | :                       | :  | :  |    |    |     |
|             | 1   | 1  | 1                       | 1  | 0  |    |    |     |
|             | 1   | 1  | 1                       | 1  | 1  |    |    |     |


| Mode  | MSB |    | Bass/Middle/Treble Boost/Cut |                         |    |    |    | LSB |
|-------|-----|----|------------------------------|-------------------------|----|----|----|-----|
|       | D7  | D6 | D5                           | D4                      | D3 | D2 | D1 | D0  |
| Boost | 0   | 0  | 0                            | Bass/Middle/Treble Gain |    |    |    |     |
| Cut   | 1   |    |                              |                         |    |    |    |     |

 : Initial condition

Select address 75 (hex)

| Mode   | MSB |    |    | Loudness Hicut |    |    |    | LSB |  |
|--------|-----|----|----|----------------|----|----|----|-----|--|
|        | D7  | D6 | D5 | D4             | D3 | D2 | D1 | D0  |  |
| Hicut1 | 0   | 0  | 0  | Loudness Gain  |    |    |    |     |  |
| Hicut2 |     | 0  | 1  |                |    |    |    |     |  |
| Hicut3 |     | 1  | 0  |                |    |    |    |     |  |
| Hicut4 |     | 1  | 1  |                |    |    |    |     |  |

| Gain        | MSB |                |    | Loudness Gain |    |    |    | LSB |  |
|-------------|-----|----------------|----|---------------|----|----|----|-----|--|
|             | D7  | D6             | D5 | D4            | D3 | D2 | D1 | D0  |  |
| 0dB         | 0   | Loudness Hicut |    | 0             | 0  | 0  | 0  | 0   |  |
| 1dB         |     |                |    | 0             | 0  | 0  | 0  | 1   |  |
| 2dB         |     |                |    | 0             | 0  | 0  | 1  | 0   |  |
| 3dB         |     |                |    | 0             | 0  | 0  | 1  | 1   |  |
| 4dB         |     |                |    | 0             | 0  | 1  | 0  | 0   |  |
| 5dB         |     |                |    | 0             | 0  | 1  | 0  | 1   |  |
| 6dB         |     |                |    | 0             | 0  | 1  | 1  | 0   |  |
| 7dB         |     |                |    | 0             | 0  | 1  | 1  | 1   |  |
| 8dB         |     |                |    | 0             | 1  | 0  | 0  | 0   |  |
| 9dB         |     |                |    | 0             | 1  | 0  | 0  | 1   |  |
| 10dB        |     |                |    | 0             | 1  | 0  | 1  | 0   |  |
| 11dB        |     |                |    | 0             | 1  | 0  | 1  | 1   |  |
| 12dB        |     |                |    | 0             | 1  | 1  | 0  | 0   |  |
| 13dB        |     |                |    | 0             | 1  | 1  | 0  | 1   |  |
| 14dB        |     |                |    | 0             | 1  | 1  | 1  | 0   |  |
| 15dB        |     |                |    | 0             | 1  | 1  | 1  | 1   |  |
| 16dB        |     |                |    | 1             | 0  | 0  | 0  | 0   |  |
| 17dB        |     |                |    | 1             | 0  | 0  | 0  | 1   |  |
| 18dB        |     |                |    | 1             | 0  | 0  | 1  | 0   |  |
| 19dB        |     |                |    | 1             | 0  | 0  | 1  | 1   |  |
| 20dB        | 1   | 0              | 1  | 0             | 0  |    |    |     |  |
| Prohibition |     |                |    | :             | :  | :  | :  | :   |  |
|             |     |                |    | 1             | 1  | 1  | 1  | 1   |  |

 : Initial Condition

(6) About Power ON Reset

Built-in IC initialization is made during power ON of the supply voltage. Please send initial data to all addresses at supply voltage on. Also, please turn ON MUTE at the set side until initial data is sent.

| Parameter                             | Symbol            | Limit |     |     | Unit | Conditions                              |
|---------------------------------------|-------------------|-------|-----|-----|------|---|
|                                       |                   | Min   | Typ | Max |      |   |
| Rise Time of VCC                      | t <sub>RISE</sub> | 33    | -   | -   | μsec | V <sub>CC</sub> rise time from 0V to 5V |
| VCC Voltage of Release Power ON Reset | V <sub>POR</sub>  | -     | 4.1 | -   | V    |   |

(7) About External Compulsory Mute Terminal

It is possible to forcibly set Mute from the outside by setting input voltage at the MUTE terminal.

| Mute Voltage Condition  | Mode     |
|-------------------------|----------|
| GND to 1.0V             | MUTE ON  |
| 2.3V to V <sub>CC</sub> | MUTE OFF |

Establish the voltage of MUTE in the condition to be defined.

Application Information

1. Function and Specifications


| Function                              | Specifications  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|---------------------------------------|---|------------|--------------|-------------------|-------------------|--------|---|---|---|--------|---|---|---|--------|---|---|---|--------|---|---|---|--------|---|---|---|--------|---|---|---|
| Input selector                        | <ul style="list-style-type: none"> <li>· (Stereo input)</li> <li>· Single-End/Diff/Full-Diff</li> </ul> (Possible to set the number of single-end/diff/full-diff as follows )   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|                                       | <table border="1"> <thead> <tr> <th></th> <th>Single-End</th> <th>Differential</th> <th>Full-Differential</th> </tr> </thead> <tbody> <tr> <td>Mode 1</td> <td>0</td> <td>3</td> <td>1</td> </tr> <tr> <td>Mode 2</td> <td>1</td> <td>2</td> <td>1</td> </tr> <tr> <td>Mode 3</td> <td>3</td> <td>1</td> <td>1</td> </tr> <tr> <td>Mode 4</td> <td>4</td> <td>0</td> <td>1</td> </tr> <tr> <td>Mode 5</td> <td>5</td> <td>1</td> <td>0</td> </tr> <tr> <td>Mode 6</td> <td>6</td> <td>0</td> <td>0</td> </tr> </tbody> </table> |            | Single-End   | Differential      | Full-Differential | Mode 1 | 0 | 3 | 1 | Mode 2 | 1 | 2 | 1 | Mode 3 | 3 | 1 | 1 | Mode 4 | 4 | 0 | 1 | Mode 5 | 5 | 1 | 0 | Mode 6 | 6 | 0 | 0 |
|                                       |   | Single-End | Differential | Full-Differential |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|                                       | Mode 1  | 0          | 3            | 1                 |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|                                       | Mode 2  | 1          | 2            | 1                 |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|                                       | Mode 3  | 3          | 1            | 1                 |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
|                                       | Mode 4  | 4          | 0            | 1                 |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Mode 5                                | 5   | 1          | 0            |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Mode 6                                | 6   | 0          | 0            |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Table.1 Combination of input selector |   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Input gain                            | <ul style="list-style-type: none"> <li>· +20dB to 0dB (1dB step)</li> <li>· Possible to use “Advanced switch” for prevention of switching noise.</li> </ul>   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Mute                                  | <ul style="list-style-type: none"> <li>· Possible to use “Advanced switch” for prevention of switching noise.</li> </ul>  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Volume                                | <ul style="list-style-type: none"> <li>· +15dB to -79dB (1dB step), -∞dB</li> <li>· Possible to use “Advanced switch” for prevention of switching noise.</li> </ul>   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Bass                                  | <ul style="list-style-type: none"> <li>· +20dB to -20dB (1dB step)</li> <li>· Q=0.5, 1, 1.5, 2</li> <li>· fo=60, 80, 100, 120Hz</li> <li>· Possible to use “Advanced switch” when changing gain</li> </ul>  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Middle                                | <ul style="list-style-type: none"> <li>· +20dB to -20dB (1dB step)</li> <li>· Q=0.75, 1, 1.25, 1.5</li> <li>· fo=500, 1k, 1.5k 2.5kHz</li> <li>· Possible to use “Advanced switch” when changing gain</li> </ul>  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Treble                                | <ul style="list-style-type: none"> <li>· +20dB to -20dB (1dB step)</li> <li>· Q=0.75, 1.25</li> <li>· fo=7.5k, 10k, 12.5k, 15kHz</li> <li>· Possible to use “Advanced switch” when changing gain</li> </ul>   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Fader                                 | <ul style="list-style-type: none"> <li>· +15dB to -79dB(1dB step), -∞dB</li> <li>· Possible to use “Advanced switch” for prevention of switching noise.</li> </ul>  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| Loudness                              | <ul style="list-style-type: none"> <li>· +20dB to 0dB(1dB step)</li> <li>· fo=250/400/800Hz</li> <li>· Possible to use “Advanced switch” for prevention of switching noise.</li> </ul>  |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |
| LPF                                   | <ul style="list-style-type: none"> <li>· fc=55/85/120/160Hz, pass</li> <li>· Phase shift (0°/180°)</li> </ul>   |            |              |                   |                   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |        |   |   |   |

2. Volume / Fader Volume Attenuation Data

| (dB) | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | (dB) | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 |
|------|----|----|----|----|----|----|----|----|------|----|----|----|----|----|----|----|----|
| +15  | 0  | 1  | 1  | 1  | 0  | 0  | 0  | 1  | -33  | 1  | 0  | 1  | 0  | 0  | 0  | 0  | 1  |
| +14  | 0  | 1  | 1  | 1  | 0  | 0  | 1  | 0  | -34  | 1  | 0  | 1  | 0  | 0  | 0  | 1  | 0  |
| +13  | 0  | 1  | 1  | 1  | 0  | 0  | 1  | 1  | -35  | 1  | 0  | 1  | 0  | 0  | 0  | 1  | 1  |
| +12  | 0  | 1  | 1  | 1  | 0  | 1  | 0  | 0  | -36  | 1  | 0  | 1  | 0  | 0  | 1  | 0  | 0  |
| +11  | 0  | 1  | 1  | 1  | 0  | 1  | 0  | 1  | -37  | 1  | 0  | 1  | 0  | 0  | 1  | 0  | 1  |
| +10  | 0  | 1  | 1  | 1  | 0  | 1  | 1  | 0  | -38  | 1  | 0  | 1  | 0  | 0  | 1  | 1  | 0  |
| +9   | 0  | 1  | 1  | 1  | 0  | 1  | 1  | 1  | -39  | 1  | 0  | 1  | 0  | 0  | 1  | 1  | 1  |
| +8   | 0  | 1  | 1  | 1  | 1  | 0  | 0  | 0  | -40  | 1  | 0  | 1  | 0  | 1  | 0  | 0  | 0  |
| +7   | 0  | 1  | 1  | 1  | 1  | 0  | 0  | 1  | -41  | 1  | 0  | 1  | 0  | 1  | 0  | 0  | 1  |
| +6   | 0  | 1  | 1  | 1  | 1  | 0  | 1  | 0  | -42  | 1  | 0  | 1  | 0  | 1  | 0  | 1  | 0  |
| +5   | 0  | 1  | 1  | 1  | 1  | 0  | 1  | 1  | -43  | 1  | 0  | 1  | 0  | 1  | 0  | 1  | 1  |
| +4   | 0  | 1  | 1  | 1  | 1  | 1  | 0  | 0  | -44  | 1  | 0  | 1  | 0  | 1  | 1  | 0  | 0  |
| +3   | 0  | 1  | 1  | 1  | 1  | 1  | 0  | 1  | -45  | 1  | 0  | 1  | 0  | 1  | 1  | 0  | 1  |
| +2   | 0  | 1  | 1  | 1  | 1  | 1  | 1  | 0  | -46  | 1  | 0  | 1  | 0  | 1  | 1  | 1  | 0  |
| +1   | 0  | 1  | 1  | 1  | 1  | 1  | 1  | 1  | -47  | 1  | 0  | 1  | 0  | 1  | 1  | 1  | 1  |
| 0    | 1  | 0  | 0  | 0  | 0  | 0  | 0  | 0  | -48  | 1  | 0  | 1  | 1  | 0  | 0  | 0  | 0  |
| -1   | 1  | 0  | 0  | 0  | 0  | 0  | 0  | 1  | -49  | 1  | 0  | 1  | 1  | 0  | 0  | 0  | 1  |
| -2   | 1  | 0  | 0  | 0  | 0  | 0  | 1  | 0  | -50  | 1  | 0  | 1  | 1  | 0  | 0  | 1  | 0  |
| -3   | 1  | 0  | 0  | 0  | 0  | 0  | 1  | 1  | -51  | 1  | 0  | 1  | 1  | 0  | 0  | 1  | 1  |
| -4   | 1  | 0  | 0  | 0  | 0  | 1  | 0  | 0  | -52  | 1  | 0  | 1  | 1  | 0  | 1  | 0  | 0  |
| -5   | 1  | 0  | 0  | 0  | 0  | 1  | 0  | 1  | -53  | 1  | 0  | 1  | 1  | 0  | 1  | 0  | 1  |
| -6   | 1  | 0  | 0  | 0  | 0  | 1  | 1  | 0  | -54  | 1  | 0  | 1  | 1  | 0  | 1  | 1  | 0  |
| -7   | 1  | 0  | 0  | 0  | 0  | 1  | 1  | 1  | -55  | 1  | 0  | 1  | 1  | 0  | 1  | 1  | 1  |
| -8   | 1  | 0  | 0  | 0  | 1  | 0  | 0  | 0  | -56  | 1  | 0  | 1  | 1  | 1  | 0  | 0  | 0  |
| -9   | 1  | 0  | 0  | 0  | 1  | 0  | 0  | 1  | -57  | 1  | 0  | 1  | 1  | 1  | 0  | 0  | 1  |
| -10  | 1  | 0  | 0  | 0  | 1  | 0  | 1  | 0  | -58  | 1  | 0  | 1  | 1  | 1  | 0  | 1  | 0  |
| -11  | 1  | 0  | 0  | 0  | 1  | 0  | 1  | 1  | -59  | 1  | 0  | 1  | 1  | 1  | 0  | 1  | 1  |
| -12  | 1  | 0  | 0  | 0  | 1  | 1  | 0  | 0  | -60  | 1  | 0  | 1  | 1  | 1  | 1  | 0  | 0  |
| -13  | 1  | 0  | 0  | 0  | 1  | 1  | 0  | 1  | -61  | 1  | 0  | 1  | 1  | 1  | 1  | 0  | 1  |
| -14  | 1  | 0  | 0  | 0  | 1  | 1  | 1  | 0  | -62  | 1  | 0  | 1  | 1  | 1  | 1  | 1  | 0  |
| -15  | 1  | 0  | 0  | 0  | 1  | 1  | 1  | 1  | -63  | 1  | 0  | 1  | 1  | 1  | 1  | 1  | 1  |
| -16  | 1  | 0  | 0  | 1  | 0  | 0  | 0  | 0  | -64  | 1  | 1  | 0  | 0  | 0  | 0  | 0  | 0  |
| -17  | 1  | 0  | 0  | 1  | 0  | 0  | 0  | 1  | -65  | 1  | 1  | 0  | 0  | 0  | 0  | 0  | 1  |
| -18  | 1  | 0  | 0  | 1  | 0  | 0  | 1  | 0  | -66  | 1  | 1  | 0  | 0  | 0  | 0  | 1  | 0  |
| -19  | 1  | 0  | 0  | 1  | 0  | 0  | 1  | 1  | -67  | 1  | 1  | 0  | 0  | 0  | 0  | 1  | 1  |
| -20  | 1  | 0  | 0  | 1  | 0  | 1  | 0  | 0  | -68  | 1  | 1  | 0  | 0  | 0  | 1  | 0  | 0  |
| -21  | 1  | 0  | 0  | 1  | 0  | 1  | 0  | 1  | -69  | 1  | 1  | 0  | 0  | 0  | 1  | 0  | 1  |
| -22  | 1  | 0  | 0  | 1  | 0  | 1  | 1  | 0  | -70  | 1  | 1  | 0  | 0  | 0  | 1  | 1  | 0  |
| -23  | 1  | 0  | 0  | 1  | 0  | 1  | 1  | 1  | -71  | 1  | 1  | 0  | 0  | 0  | 1  | 1  | 1  |
| -24  | 1  | 0  | 0  | 1  | 1  | 0  | 0  | 0  | -72  | 1  | 1  | 0  | 0  | 1  | 0  | 0  | 0  |
| -25  | 1  | 0  | 0  | 1  | 1  | 0  | 0  | 1  | -73  | 1  | 1  | 0  | 0  | 1  | 0  | 0  | 1  |
| -26  | 1  | 0  | 0  | 1  | 1  | 0  | 1  | 0  | -74  | 1  | 1  | 0  | 0  | 1  | 0  | 1  | 0  |
| -27  | 1  | 0  | 0  | 1  | 1  | 0  | 1  | 1  | -75  | 1  | 1  | 0  | 0  | 1  | 0  | 1  | 1  |
| -28  | 1  | 0  | 0  | 1  | 1  | 1  | 0  | 0  | -76  | 1  | 1  | 0  | 0  | 1  | 1  | 0  | 0  |
| -29  | 1  | 0  | 0  | 1  | 1  | 1  | 0  | 1  | -77  | 1  | 1  | 0  | 0  | 1  | 1  | 0  | 1  |
| -30  | 1  | 0  | 0  | 1  | 1  | 1  | 1  | 0  | -78  | 1  | 1  | 0  | 0  | 1  | 1  | 1  | 0  |
| -31  | 1  | 0  | 0  | 1  | 1  | 1  | 1  | 1  | -79  | 1  | 1  | 0  | 0  | 1  | 1  | 1  | 1  |
| -32  | 1  | 0  | 1  | 0  | 0  | 0  | 0  | 0  | -∞   | 1  | 1  | 1  | 1  | 1  | 1  | 1  | 1  |

 : Initial condition

3. Application Circuit



Unit  
 R : [Ω]  
 C : [F]

(Note) About single input 1 to 3, it is possible to change from single input to GND Isolation input 2,3.

(Note) About GND Isolation1 and Full Differential, it is possible to change from differential input to single input 4 to 6.

Notes on wiring

- ① Please connect the decoupling capacitor of the power supply in the shortest possible distance to GND.
- ② GND lines should be one-point connected.
- ③ Wiring pattern of Digital shall be away from that of analog unit and crosstalk should not be acceptable.
- ④ If possible, SCL and SDA lines of I<sup>2</sup>C BUS should not be in parallel.  
The lines should be shielded, if they are adjacent to each other.
- ⑤ If possible, analog input lines should not be in parallel. The lines should be shielded, if they are adjacent to each other.
- ⑥ TEST pins (Pin 14,15,16) should be OPEN.

Power Dissipation

About the thermal design of the IC

Characteristics of an IC are greatly affected by the temperature at which it is used. Exceeding absolute maximum ratings may degrade and destroy the device. Careful consideration must be given to the heat of the IC from the two standpoints of immediate damage and long-term reliability of operation.




Figure 23. Temperature Derating Curve

(Note) Values are actual measurements and are not guaranteed.

Power dissipation values vary according to the board on which the IC is mounted.

I/O Equivalent Circuits

| Terminal No.                        | Terminal Name                                      | Terminal Voltage | Equivalent Circuit | Terminal Description   |
|-------------------------------------|--|------------------|--------------------|--|
| 1<br>2<br>3<br>4<br>5<br>6          | A1<br>A2<br>B1<br>B2<br>C1<br>C2                   | 4.25             |                    | A terminal for signal input.<br>The input impedance is 100kΩ (Typ).  |
| 7<br>8<br>9<br>10<br>11<br>12<br>13 | DP1<br>DN<br>DP2<br>EP1<br>EN1<br>EN2<br>EP2       | 4.25             |                    | Input terminal available to single/Differential mode.<br>The input impedance is 250kΩ (Typ).   |
| 15                                  | MUTE   | -                |                    | A terminal for external compulsory mute. If terminal voltage is High level, the mute is OFF. And if the terminal voltage is Low level, the mute is ON. |
| 18<br>19<br>20<br>21<br>22<br>23    | OUTS2<br>OUTS1<br>OUTR2<br>OUTR1<br>OUTF2<br>OUTF1 | 4.25             |                    | A terminal for fader and Subwoofer output.   |

Values in the pin explanation and input/output equivalent circuit are for reference purposes only. It is not a guaranteed value.



I/O Equivalent Circuits - continued

| Terminal No.   | Terminal Name | Terminal Voltage | Equivalent Circuit | Terminal Description   |
|----------------|---------------|------------------|--------------------|--|
| 24             | VCC           | 8.5              |                    | Power supply terminal.   |
| 25             | SCL           | -                |                    | A terminal for clock input of I <sup>2</sup> C BUS communication.  |
| 26             | SDA           | -                |                    | A terminal for data input of I <sup>2</sup> C BUS communication.   |
| 27             | GND           | 0                |                    | Ground terminal.   |
| 28             | FIL           | 4.25             |                    | Voltage for reference bias of analog signal system. The simple pre-charge circuit and simple discharge circuit for an external capacitor are built in. |
| 14<br>16<br>17 | TEST          | -                |                    | TEST terminal  |

Values in the pin explanation and input/output equivalent circuit are for reference purposes only. It is not a guaranteed value.

## Operational Notes

### 1. Reverse Connection of Power Supply

Connecting the power supply in reverse polarity can damage the IC. Take precautions against reverse polarity when connecting the power supply, such as mounting an external diode between the power supply and the IC's power supply pins.

### 2. Power Supply Lines

Design the PCB layout pattern to provide low impedance supply lines. Separate the ground and supply lines of the digital and analog blocks to prevent noise in the ground and supply lines of the digital block from affecting the analog block. Furthermore, connect a capacitor to ground at all power supply pins. Consider the effect of temperature and aging on the capacitance value when using electrolytic capacitors.

### 3. Ground Voltage

Ensure that no pins are at a voltage below that of the ground pin at any time, even during transient condition.

### 4. Ground Wiring Pattern

When using both small-signal and large-current ground traces, the two ground traces should be routed separately but connected to a single ground at the reference point of the application board to avoid fluctuations in the small-signal ground caused by large currents. Also ensure that the ground traces of external components do not cause variations on the ground voltage. The ground lines must be as short and thick as possible to reduce line impedance.

### 5. Thermal Consideration

Should by any chance the power dissipation rating be exceeded the rise in temperature of the chip may result in deterioration of the properties of the chip. In case of exceeding this absolute maximum rating, increase the board size and copper area to prevent exceeding the Pd rating.

### 6. Recommended Operating Conditions

These conditions represent a range within which the expected characteristics of the IC can be approximately obtained. The electrical characteristics are guaranteed under the conditions of each parameter.

### 7. Inrush Current

When power is first supplied to the IC, it is possible that the internal logic may be unstable and inrush current may flow instantaneously due to the internal powering sequence and delays, especially if the IC has more than one power supply. Therefore, give special consideration to power coupling capacitance, power wiring, width of ground wiring, and routing of connections.

### 8. Operation Under Strong Electromagnetic Field

Operating the IC in the presence of a strong electromagnetic field may cause the IC to malfunction.

### 9. Testing on Application Boards

When testing the IC on an application board, connecting a capacitor directly to a low-impedance output pin may subject the IC to stress. Always discharge capacitors completely after each process or step. The IC's power supply should always be turned off completely before connecting or removing it from the test setup during the inspection process. To prevent damage from static discharge, ground the IC during assembly and use similar precautions during transport and storage.

### 10. Inter-pin Short and Mounting Errors

Ensure that the direction and position are correct when mounting the IC on the PCB. Incorrect mounting may result in damaging the IC. Avoid nearby pins being shorted to each other especially to ground, power supply and output pin. Inter-pin shorts could be due to many reasons such as metal particles, water droplets (in very humid environment) and unintentional solder bridge deposited in between pins during assembly to name a few.

### 11. Unused Input Pins

Input pins of an IC are often connected to the gate of a MOS transistor. The gate has extremely high impedance and extremely low capacitance. If left unconnected, the electric field from the outside can easily charge it. The small charge acquired in this way is enough to produce a significant effect on the conduction through the transistor and cause unexpected operation of the IC. So unless otherwise specified, unused input pins should be connected to the power supply or ground line.

Operational Notes – continued

12. Regarding the Input Pin of the IC

This monolithic IC contains P+ isolation and P substrate layers between adjacent elements in order to keep them isolated. P-N junctions are formed at the intersection of the P layers with the N layers of other elements, creating a parasitic diode or transistor. For example (refer to figure below):

When GND > Pin A and GND > Pin B, the P-N junction operates as a parasitic diode.  
 When GND > Pin B, the P-N junction operates as a parasitic transistor.

Parasitic diodes inevitably occur in the structure of the IC. The operation of parasitic diodes can result in mutual interference among circuits, operational faults, or physical damage. Therefore, conditions that cause these diodes to operate, such as applying a voltage lower than the GND voltage to an input pin (and thus to the P substrate) should be avoided.





Figure 24. Example of monolithic IC structure

13. About a Signal Input Part

(a) About Input Coupling Capacitor Constant Value

The constant value of input coupling capacitor C(F) is decided with respect to the input impedance  $R_{IN}(\Omega)$  at the input signal terminal of the IC that would be sufficient to form an RC characterized HPF.



(b) About the Input Selector SHORT

SHORT mode is the command which makes switch  $S_{SH} = ON$  of input selector part so that the input impedance  $R_{IN}$  of all terminals becomes small. Switch  $S_{SH}$  is OFF when SHORT command is not selected. The constant time brought about by the small resistance inside and the capacitor outside the LSI becomes small when this command is used. The charge time of the capacitor becomes short. Since SHORT mode turns ON the switch of  $S_{SH}$  and makes it low impedance, please use it at no signal condition.


14. About Mute Terminal (Pin 15) when Power Supply is OFF

There should be no applied voltage to Mute terminal (Pin 15) when power-supply is OFF. If in case voltage is supplied to Mute terminal, please insert a series resistor (about 2.2kΩ) to Mute terminal. (Please refer to Application Circuit Diagram.)


15. About TEST Pin

TEST Pin should be OPEN.  
 Pin 14, 16, 17 are TEST Pins


Ordering Information



Marking Diagram



Physical Dimension, Tape and Reel Information



## Revision History

| Date        | Revision | Changes     |
|-------------|----------|-------------|
| 16.Dec.2015 | 001      | New Release |

# Notice

## Precaution on using ROHM Products

- Our Products are designed and manufactured for application in ordinary electronic equipments (such as AV equipment, OA equipment, telecommunication equipment, home electronic appliances, amusement equipment, etc.). If you intend to use our Products in devices requiring extremely high reliability (such as medical equipment <sup>(Note 1)</sup>, transport equipment, traffic equipment, aircraft/spacecraft, nuclear power controllers, fuel controllers, car equipment including car accessories, safety devices, etc.) and whose malfunction or failure may cause loss of human life, bodily injury or serious damage to property ("Specific Applications"), please consult with the ROHM sales representative in advance. Unless otherwise agreed in writing by ROHM in advance, ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties arising from the use of any ROHM's Products for Specific Applications.

(Note1) Medical Equipment Classification of the Specific Applications

| JAPAN     | USA       | EU         | CHINA     |
|-----------|-----------|------------|-----------|
| CLASS III | CLASS III | CLASS II b | CLASS III |
| CLASS IV  |           | CLASS III  |           |

- ROHM designs and manufactures its Products subject to strict quality control system. However, semiconductor products can fail or malfunction at a certain rate. Please be sure to implement, at your own responsibilities, adequate safety measures including but not limited to fail-safe design against the physical injury, damage to any property, which a failure or malfunction of our Products may cause. The following are examples of safety measures:
  - Installation of protection circuits or other protective devices to improve system safety
  - Installation of redundant circuits to reduce the impact of single or multiple circuit failure
- Our Products are designed and manufactured for use under standard conditions and not under any special or extraordinary environments or conditions, as exemplified below. Accordingly, ROHM shall not be in any way responsible or liable for any damages, expenses or losses arising from the use of any ROHM's Products under any special or extraordinary environments or conditions. If you intend to use our Products under any special or extraordinary environments or conditions (as exemplified below), your independent verification and confirmation of product performance, reliability, etc. prior to use, must be necessary:
  - Use of our Products in any types of liquid, including water, oils, chemicals, and organic solvents
  - Use of our Products outdoors or in places where the Products are exposed to direct sunlight or dust
  - Use of our Products in places where the Products are exposed to sea wind or corrosive gases, including Cl<sub>2</sub>, H<sub>2</sub>S, NH<sub>3</sub>, SO<sub>2</sub>, and NO<sub>2</sub>
  - Use of our Products in places where the Products are exposed to static electricity or electromagnetic waves
  - Use of our Products in proximity to heat-producing components, plastic cords, or other flammable items
  - Sealing or coating our Products with resin or other coating materials
  - Use of our Products without cleaning residue of flux (even if you use no-clean type fluxes, cleaning residue of flux is recommended); or Washing our Products by using water or water-soluble cleaning agents for cleaning residue after soldering
  - Use of the Products in places subject to dew condensation
- The Products are not subject to radiation-proof design.
- Please verify and confirm characteristics of the final or mounted products in using the Products.
- In particular, if a transient load (a large amount of load applied in a short period of time, such as pulse. is applied, confirmation of performance characteristics after on-board mounting is strongly recommended. Avoid applying power exceeding normal rated power; exceeding the power rating under steady-state loading condition may negatively affect product performance and reliability.
- De-rate Power Dissipation depending on ambient temperature. When used in sealed area, confirm that it is the use in the range that does not exceed the maximum junction temperature.
- Confirm that operation temperature is within the specified range described in the product specification.
- ROHM shall not be in any way responsible or liable for failure induced under deviant condition from what is defined in this document.

## Precaution for Mounting / Circuit board design

- When a highly active halogenous (chlorine, bromine, etc.) flux is used, the residue of flux may negatively affect product performance and reliability.
- In principle, the reflow soldering method must be used on a surface-mount products, the flow soldering method must be used on a through hole mount products. If the flow soldering method is preferred on a surface-mount products, please consult with the ROHM representative in advance.

For details, please refer to ROHM Mounting specification

**Precautions Regarding Application Examples and External Circuits**

1. If change is made to the constant of an external circuit, please allow a sufficient margin considering variations of the characteristics of the Products and external components, including transient characteristics, as well as static characteristics.
2. You agree that application notes, reference designs, and associated data and information contained in this document are presented only as guidance for Products use. Therefore, in case you use such information, you are solely responsible for it and you must exercise your own independent verification and judgment in the use of such information contained in this document. ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties arising from the use of such information.

**Precaution for Electrostatic**

This Product is electrostatic sensitive product, which may be damaged due to electrostatic discharge. Please take proper caution in your manufacturing process and storage so that voltage exceeding the Products maximum rating will not be applied to Products. Please take special care under dry condition (e.g. Grounding of human body / equipment / solder iron, isolation from charged objects, setting of Ionizer, friction prevention and temperature / humidity control).

**Precaution for Storage / Transportation**

1. Product performance and soldered connections may deteriorate if the Products are stored in the places where:
  - [a] the Products are exposed to sea winds or corrosive gases, including Cl<sub>2</sub>, H<sub>2</sub>S, NH<sub>3</sub>, SO<sub>2</sub>, and NO<sub>2</sub>
  - [b] the temperature or humidity exceeds those recommended by ROHM
  - [c] the Products are exposed to direct sunshine or condensation
  - [d] the Products are exposed to high Electrostatic
2. Even under ROHM recommended storage condition, solderability of products out of recommended storage time period may be degraded. It is strongly recommended to confirm solderability before using Products of which storage time is exceeding the recommended storage time period.
3. Store / transport cartons in the correct direction, which is indicated on a carton with a symbol. Otherwise bent leads may occur due to excessive stress applied when dropping of a carton.
4. Use Products within the specified time after opening a humidity barrier bag. Baking is required before using Products of which storage time is exceeding the recommended storage time period.

**Precaution for Product Label**

QR code printed on ROHM Products label is for ROHM's internal use only.

**Precaution for Disposition**

When disposing Products please dispose them properly using an authorized industry waste company.

**Precaution for Foreign Exchange and Foreign Trade act**

Since concerned goods might be fallen under listed items of export control prescribed by Foreign exchange and Foreign trade act, please consult with ROHM in case of export.

**Precaution Regarding Intellectual Property Rights**

1. All information and data including but not limited to application example contained in this document is for reference only. ROHM does not warrant that foregoing information or data will not infringe any intellectual property rights or any other rights of any third party regarding such information or data.
2. ROHM shall not have any obligations where the claims, actions or demands arising from the combination of the Products with other articles such as components, circuits, systems or external equipment (including software).
3. No license, expressly or implied, is granted hereby under any intellectual property rights or other rights of ROHM or any third parties with respect to the Products or the information contained in this document. Provided, however, that ROHM will not assert its intellectual property rights or other rights against you or your customers to the extent necessary to manufacture or sell products containing the Products, subject to the terms and conditions herein.

**Other Precaution**

1. This document may not be reprinted or reproduced, in whole or in part, without prior written consent of ROHM.
2. The Products may not be disassembled, converted, modified, reproduced or otherwise changed without prior written consent of ROHM.
3. In no event shall you use in any way whatsoever the Products and the related technical information contained in the Products or this document for any military purposes, including but not limited to, the development of mass-destruction weapons.
4. The proper names of companies or products described in this document are trademarks or registered trademarks of ROHM, its affiliated companies or third parties.



**General Precaution**

1. Before you use our Products, you are requested to carefully read this document and fully understand its contents. ROHM shall not be in any way responsible or liable for failure, malfunction or accident arising from the use of any ROHM's Products against warning, caution or note contained in this document.
2. All information contained in this document is current as of the issuing date and subject to change without any prior notice. Before purchasing or using ROHM's Products, please confirm the latest information with a ROHM sales representative.
3. The information contained in this document is provided on an "as is" basis and ROHM does not warrant that all information contained in this document is accurate and/or error-free. ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties resulting from inaccuracy or errors of or concerning such information.

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[ROHM Semiconductor:](#)

[BD37532FV-E2](#)