



### Main

Range	TeSys
Device short name	LB6LD
Range compatibility	TeSys Integral contactor breaker
Product or component type	Protection module
Poles description	3P
Utilisation category	AC-43
System Voltage	690 V AC
Magnetic tripping current	240...480 A
Trip unit technology	Magnetic
Protection type	Phase imbalance

### Complementary

Motor power kW	22 kW at 400...415 V AC 50/60 Hz 22 kW at 440 V AC 50/60 Hz 25 kW at 480...525 V AC 50/60 Hz 33 kW at 600...690 V AC 50/60 Hz 9 kW at 220...240 V AC 50/60 Hz
Product weight	1.72 lb(US) (0.78 kg)

### Environment

standards	NF C 63-650
protective treatment	TH
IP degree of protection	IP20 B conforming to IEC 60144 IP20 B conforming to IEC 60529
ambient air temperature for operation	-4...140 °F (-20...60 °C)

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0841 - Schneider Electric declaration of conformity	Compliant - since 0841 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

### Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.