



| SPECIFICATIONS | | | | | | | | | | | |
|---|-------|-------|---------------------|-----------------------|--|-------------------------|------------------------------------|--|-------------------|-------------------|--------|
| WIRING | INPUT | | OUTPUT | | | | SHAFT ROTATION TO INCREASE VOLTAGE | TERMINAL CONNECTIONS | | | |
| | VOLTS | HERTZ | VOLTS | CONSTANT CURRENT LOAD | | CONSTANT IMPEDANCE LOAD | | FOR INCREASING VOLTAGE AS VIEWED FROM BASE END | | | |
| | | | | MAX. AMPS | MAX. KVA | MAX. AMPS | | MAX. KVA | INPUT | JUMPER | OUTPUT |
| SINGLE PHASE | 240 | 60 | 0-240 | 5.0 | 1.20 | 7.0 | 1.68 | CW | 1-4 | 4-3 | |
| | | | | | | | | CCW | 1-4 | 1-3 | |
| <small>UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS .03 HOLES .002 ANGLES 1° DRAFT 1-1/2° XX .005 XXX .005</small> | | | | | | | | | | | |
| MATERIAL: | | | UNITS IN [mm] | | TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1220B | | | | | | |
| ALL DIMENSIONS APPLY AFTER PLATING | | | DRAWN BY S.A. SMITH | | DATE 9/25/97 | | FIRST USED ON | | DO NOT SCALE DWG. | | |
| The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts. | | | CHECKER | | DATE | | WEIGHT APPROX. 9 LBS | | CAGE CODE 83008 | | |
| | | | ENGINEER | | DATE | | SCALE 1=1 | | SHEET 1 OF 1 | | |
| | | | | | | | | | | DWG. NO. 031-3260 | |