

Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

Complementary

System Voltage	120 V AC at 50/60 Hz
[Ie] rated operational current AC	15 A
Motor power hp	40 hp at 208 V AC for 3 phases motors 50 hp at 230 V AC for 3 phases motors 100 hp at 460 V AC for 3 phases motors 100 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Location of connection	Line

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1444 - Schneider Electric declaration of conformity	Compliant - since 1444 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.