



Main

| | |
|---------------------------------------|------------------------------------|
| Range of product | 8501X |
| Relay type | Latching |
| Product or component type | Relay |
| [In] rated current | 10 A AC 5 A DC |
| Contacts type and composition | 8 NO 8 standard contact cartridges |
| Poles description | 8P |
| [Uc] control circuit voltage | 115/125 V DC |
| Maximum switching voltage | 250 V DC |
| Mounting support | Panel |
| Ambient air temperature for operation | -40...160 °F |
| Electrical connection | Screw clamp terminals |
| Product certifications | CE CSA UL listed |
| Operating time | 37 ms pick-up 45 ms drop-out |

Complementary

Environment

Offer Sustainability

| | |
|--|--|
| Green Premium product | Green Premium product |
| Compliant - since 1332 - Schneider Electric declaration of conformity | Compliant - since 1332 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Available | Available |
| WARNING: This product can expose you to chemicals including: | WARNING: This product can expose you to chemicals including: |
| Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. | Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. |
| For more information go to www.p65warnings.ca.gov | For more information go to www.p65warnings.ca.gov |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.