XCNR2118G11





Main

| Range of product | OsiSense XC |
|---------------------------------------|--|
| Series name | Standard format |
| Product or component type | Limit switch |
| Device short name | XCNR |
| Sensor design | Compact |
| Reset | With |
| Body type | Fixed |
| Head type | Rotary head |
| Material | Plastic |
| Body material | Plastic |
| Head material | Plastic |
| Fixing mode | By the body |
| Movement of operating head | Rotary |
| Type of operator | Spring return roller lever thermoplastic |
| Type of approach | Lateral approach 2 directions |
| Number of poles | 2 |
| Contacts type and composition | 1 NC + 1 NO |
| Contact operation | Snap action |
| · · · · · · · · · · · · · · · · · · · | |

Complementary

| Switch actuation | By 30° cam |
|--|---|
| Electrical connection | Screw-clamp terminals, clamping capacity: 1 x 0.342 x 1.5 mm ² |
| Cable entry | 1 entry tapped for Pg 11 cable gland |
| Contacts insulation form | Zb |
| Positive opening | With |
| Positive opening minimum torque | 1.33 lbf.in (0.15 N.m) |
| Minimum torque for tripping | 0.88 lbf.in (0.1 N.m) |
| Maximum actuation speed | 4.92 ft/s (1.5 m/s) |
| Contact code designation | R300, DC-13 (Ue = 250 V, Ie = 0.1 A) conforming to EN/IEC 60947-5-1 appendix A A300, AC-15 (Ue = 240 V, Ie = 3 A) , Ithe = 10 A conforming to EN/IEC 60947-5-1 appendix A |
| [Ui] rated insulation voltage | 300 V conforming to UL 508 500 V degree of pollution 3 conforming to EN/IEC 60947-1 300 V conforming to CSA C22.2 No 14 |
| [Uimp] rated impulse withstand voltage | 6 kV conforming to IEC 60664 6 kV conforming to IEC 60947-1 |
| Short-circuit protection | 10 A cartridge fuse type gG |
| Mechanical durability | 100000 cycles |

Environment

| 50 gn (duration = 11 ms) conforming to IEC 60068-2-27 |
|--|
| |
| 25 gn 10500 Hz IEC 60068-2-6 |
| IP65 conforming to IEC 60529 |
| IK04 conforming to EN 50102 |
| Class II conforming to IEC 61140 Class II conforming to NF C 20030 |
| -13158 °F (-2570 °C) |
| -40158 °F (-4070 °C) |
| - |

| protective treatment | TC | |
|------------------------|------------------------------|--|
| product certifications | CCC CSA UL | |
| standards | EN 60204-1 EN 60947-5-1 | |
| | IEC 60204-1 IEC 60947-5-1 | |
| | UL 508 CSA C22.2 No 14 | |


Offer Sustainability

| Green Premium product | Green Premium product |
|--|---|
| Compliant - since 1002 - Schneider Electric declaration of conformity | Compliant - since 1002 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| WARNING: This product can expose you to chemicals including: | WARNING: This product can expose you to chemicals including: |
| Diisononyl phthalate (DINP), which is known to the State of California to cause cancer, and | Diisononyl phthalate (DINP), which is known to the State of California to cause cancer, and |
| Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. | eDi-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. |
| For more information go to www.p65warnings.ca.gov | For more information go to www.p65warnings.ca.gov |

Contractual warranty

| Warranty period | 18 months |
|-----------------|-----------|
|-----------------|-----------|


Dimensions



- (1) 1 tapped entry for Pg 11 cable gland
- (2) \varnothing : 2 elongated holes \varnothing 4.3 x 6.3 on 22 mm centres, 2 holes \varnothing 4.3 on 20 mm centres.

Mounting with Cable Entry


Position of Cable Gland




(1) Recommended

Mounting with Rotary Heads and Levers

Type of Cam





- (1) Recommended
- (2) To be avoided


Wiring Diagrams

2-pole NC + NO Snap Action




Characteristics of Actuation

Switch Actuation by 30° Cam



Functionnal Diagram



- (P) Positive opening point
- (1) NC contact with positive opening operation
- Closed (2)
- (3) Open
- (4) Tripping
- (5) Resetting