



Jul.1.2019 Copyright 2019 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.



ASSEMBLED DIAGRAM
(2 : 1)





2 TABLE-1

APPLICABLE CABLE WIRE			
CONFIGURATION (FOR REF.)		INSULATOR DIAMETER	φ0.90 ~ 1.00
		CONDUCTOR	φ0.4 ~ 0.65 SOLID WIRE

3 TABLE-2

TYPE	PART NO.
APPLICATOR	BTA-104
HANDTOOL BODY	#901520




NOTE 1 THE DIMENSIONS IN PARENTHESIS ARE FOR REFERENCE.

2 APPLICABLE CABLE IS SHOWN IN TABLE-1.

3 HIROSE'S SPECIAL ASSEMBLY TOOL MUST BE USED TO ASSEMBLE THIS CONNECTOR.
(REFER TO TABLE-2)

4 CONTACT HEIGHT h AFTER ASSEMBLY SHALL BE 5.89 TO 6.14.



1	POLYCARBONATE	(CLEAR) UL94V-0	2	PHOSPHOR BRONZE	GOLD PLATING 1.27 μm min
NO.	MATERIAL	FINISH , REMARKS	NO.	MATERIAL	FINISH , REMARKS
UNITS mm		SCALE 4 : 1	COUNT 3	DESCRIPTION OF REVISIONS DIS-E-003191	DESIGNED YH.MAMADA
		APPROVED : HO.MIWA	06.01.27	DRAWING NO.	EDC3-043131-01
		CHECKED : YH.ENAMI	06.01.27	PART NO.	TM20P-88P
		DESIGNED : TS.ITO	06.01.23	CODE NO.	CL222-2217-7-00
		DRAWN : TS.ITO	06.01.23		
					10.03.16