



### Contents

Device	Part number	Quantity
Cable assembly RPC-7 / RPC-7	LU7-070-600	2

### Documents

Technical data sheet cable assembly:  
RPC-7 / RPC-7

LU7-070-XXX

**Electrical data**

Impedance	50 Ω
Frequency	DC to 18 GHz
Return loss	≥ 28 dB, DC to 4 GHz ≥ 20 dB, 4 GHz to 18 GHz
Insertion loss	≤ 1.30 dB at 18 GHz
Phase deviation:	
After 90° bending	≤ 0.5°, DC to 4 GHz ≤ 2.0°, 4 GHz to 18 GHz
Straight after 3x90° bending	≤ 0.5°, DC to 4 GHz ≤ 1.5°, 4 GHz to 18 GHz
Amplitude stability	≤ 0.03 dB, DC to 4 GHz ≤ 0.05 dB, 4 GHz to 18 GHz
Return loss stability	≥ 48 dB, DC to 4 GHz ≥ 40 dB, 4 GHz to 18 GHz
RF-leakage	≥ 100 dB up to 1 GHz

**Mechanical data**

Minimum bend radius	60 mm
---------------------	-------

**Environmental data**

Temperature range	-40°C to +85°C
2002/95/EC (RoHS)	compliant

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Herbert Babinger	24/02/06	Frank Tatzel	28/02/11	e00	11-0169	Krautenbacher J.	28/02/11
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany <a href="http://www.rosenberger.de">www.rosenberger.de</a>					Tel.: +49 8684 18-0 Fax: +49 8684 18-499 email: <a href="mailto:info@rosenberger.de">info@rosenberger.de</a>		Page 2 / 2