

Small Signal Transistors

TO-39 Case



TYPE NO.	DESCRIPTION	V _{CB0}	V _{CE0}	V _{EBO}	I _{CBO} @ I _{CEO} I _{ICES} I _{CEV} I _{CER}	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE(SAT)}	@ I _C	f _T	C _{ob}	t _{on}	t _{off}	NF	
		(V)	(V)	(V)			(V)	(V)	(V)	(V)	(V)	(V)	(mA)	(MHz)	(pF)	(ns)	(ns)	(dB)
		MIN	*V _{CER} MIN	MIN			MIN	MIN	MIN	MAX	(mA)	(V)	MAX	(mA)	MIN	MAX	MAX	MAX
2N656A	NPN AMPL/SWITCH	60	60	6.0	10	30	30	90	200	10	2.00	200	50	20	--	--	--	
2N657A	NPN AMPL/SWITCH	100	100	6.0	10	30	30	90	200	10	2.00	200	50	20	--	--	--	
2N696	NPN AMPL/SWITCH	60	40	5.0	1.00	30	20	60	150	10	1.50	150	80	35	--	--	--	
2N697A	NPN AMPL/SWITCH	60	35	5.0	1.00	30	40	120	150	10	1.50	150	50	35	--	--	--	
2N698	NPN AMPL/SWITCH	120	60	7.0	0.05	75	20	60	150	10	1.50	150	50	15	--	--	--	
2N699B	NPN AMPL/SWITCH	120	80	7.0	0.01	90	40	120	150	10	1.30	150	60	15	--	--	--	
2N1052	NPN HIGH VOLTAGE	200	155	6.0	10	200	20	80	200	6.0	5.00	200	8.0	50	--	--	--	
2N1053	NPN AMPL/SWITCH	180	135	6.0	10	180	20	80	200	6.0	5.00	200	8.0	50	--	--	--	
2N1054	NPN AMPL/SWITCH	125	115	6.0	5.00	125	20	--	200	6.0	4.00	200	8.0	50	--	--	--	
2N1055	NPN AMPL/SWITCH	100	100	6.0	15	100	20	80	50	6.0	2.00	50	3.0	--	--	--	--	
2N1116	NPN AMPL/SWITCH	60	60	6.0	15	60	40	150	500	6.0	5.00	500	6.0	80	--	--	--	
2N1117	NPN AMPL/SWITCH	60	60	6.0	15	60	40	150	200	6.0	4.00	200	4.0	--	--	--	--	
2N1118	PNP AMPL/SWITCH	25	25	6.0	1.00	25	15	--	1.0	6.0	--	--	12	--	--	--	--	
2N1119	PNP AMPL/SWITCH	10	10	6.0	0.10	10	15	--	15	0.5	0.15	5.0	--	12	--	--	--	
2N1131	PNP AMPL/SWITCH	50	35	5.0	100	50	20	45	150	10	1.50	150	50	45	--	--	--	
2N1131A	PNP AMPL/SWITCH	60	40	5.0	0.50	45	20	45	150	10	1.50	150	90	45	--	--	--	
2N1132B	PNP AMPL/SWITCH	70	50	6.0	0.10	50	30	75	150	10	1.50	150	90	30	--	--	--	
2N1258	PNP AMPL/SWITCH	30	30	5.0	0.20	20	75	150	10	1.0	0.60	10	--	10	--	--	--	
2N1259	PNP AMPL/SWITCH	50	50	5.0	0.20	30	25	100	10	1.0	0.30	10	--	10	--	--	--	
2N1420	NPN AMPL/SWITCH	60	30	5.0	1.00	30	100	300	150	10	1.50	150	50	35	--	--	--	
2N1445	NPN AMPL/SWITCH	120	120	6.0	10	120	20	80	200	10	4.00	200	--	--	--	--	--	
2N1479	NPN AMPL/SWITCH	60	40	6.0	10	30	20	60	200	4.0	1.40	200	1.5	--	--	--	--	
2N1480	NPN AMPL/SWITCH	100	55	6.0	10	30	20	60	200	4.0	1.40	200	1.5	--	--	--	--	
2N1481	NPN AMPL/SWITCH	60	40	6.0	10	30	35	100	200	4.0	1.40	200	1.5	--	--	--	--	
2N1482	NPN AMPL/SWITCH	100	55	6.0	10	30	35	100	200	4.0	1.40	200	1.5	--	--	--	--	
2N1507	NPN AMPL/SWITCH	60	25	5.0	1.00	30	100	300	150	10	1.50	150	50	35	--	--	--	
2N1573	NPN AMPL/SWITCH	125	80	5.0	1.00	40	30	100	5.0	5.0	1.00	10	60	10	--	--	--	
2N1574	NPN AMPL/SWITCH	125	80	5.0	1.00	40	60	200	5.0	5.0	1.00	10	60	10	--	--	--	
2N1613B	NPN AMPL/SWITCH	120	50	7.0	0.10	60	40	120	150	10	0.20	150	60	10	--	--	--	
2N1615	NPN AMPL/SWITCH	100	100	6.0	2.00	60	25	--	5.0	10	5.00	50	5.0	20	--	--	--	
2N1676	PNP AMPL/SWITCH	4.5	4.5	4.5	0.10	4.5	25	--	2.0	0.2	1.50	10	40	7.0	--	--	--	
2N1700	NPN AMPL/SWITCH	60	40	6.0	75	40	20	80	100	4.0	1.00	100	--	--	--	--	--	
2N1711	NPN AMPL/SWITCH	75	50	7.0	0.10	60	100	300	150	10	1.00	150	70	25	--	--	--	
2N1711B	NPN AMPL/SWITCH	120	50	7.0	0.10	60	100	300	150	10	0.20	150	70	10	--	--	--	
2N1716	NPN AMPL/SWITCH	60	60	6.0	2.00	60	40	120	200	5.0	2.00	200	16	50	--	--	--	
2N1717	NPN AMPL/SWITCH	100	100	6.0	1.00	75	40	120	200	5.0	2.00	200	16	50	--	--	--	
2N1889	NPN AMPL/SWITCH	100	60	7.0	0.10	75	40	120	150	10	5.00	150	50	15	--	--	--	
2N1890	NPN AMPL/SWITCH	100	60	7.0	0.10	75	100	300	150	10	1.20	50	60	15	--	--	--	
2N1893A	NPN AMPL/SWITCH	140	80	7.0	0.10	90	40	120	150	10	2.00	150	100	8.0	--	--	--	
2N1973	NPN AMPL/SWITCH	100	60	7.0	0.025	75	75	--	10	10	1.20	50	60	15	--	--	--	
2N1974	NPN AMPL/SWITCH	100	60	7.0	0.025	75	35	--	10	10	1.20	50	50	15	--	--	--	

(5-April 2013)

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centalsemi.com

Worldwide Field Representatives:
www.centalsemi.com/wwreps

Worldwide Distributors:
www.centalsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centalsemi.com/terms