

# Contactor

## 3 Pole / Frame Size 400AF



**Altech Corp.®**

includes 2 x AU-100-11  
Auxiliary switch,  
(2NO/2NC)

Additional Auxiliaries  
and other accessories  
see page 11-13

| Type                 | MC-265A | MC-330A | MC-400A |
|----------------------|---------|---------|---------|
| Number of Poles      | 3       | 3       | 3       |
| NEMA Size            | 5       | 5       | 5       |
| Standard Auxiliaries | 2NO/2NC | 2NO/2NC | 2NO/2NC |

|                             | Coil Voltage      |           | Part. No.        | Part. No.        | Part. No.        |
|-----------------------------|-------------------|-----------|------------------|------------------|------------------|
| <b>AC/DC</b><br>Common Coil | <b>AC 50/60Hz</b> | <b>DC</b> |                  |                  |                  |
|                             | 100-240V          | 100-220V  | MC-265A-100/200V | MC-330A-100/200V | MC-400A-100/200V |
|                             | 265-347V          | –         | MC-265A-300V     | MC-330A-300V     | MC-400A-300V     |
|                             | 380-450V          | –         | MC-265A-400V     | MC-330A-400V     | MC-400A-400V     |
|                             | 440-575V          | –         | MC-265A-500V     | MC-330A-500V     | MC-400A-500V     |

| HP Rating / UL508 |                    | HP   | HP   | HP   |
|-------------------|--------------------|------|------|------|
|                   | Continuous current | 300A | 350A | 450A |
| Single phase      | 110~120V           | –    | –    | –    |
|                   | 220~240V           | –    | –    | –    |
| Three phase       | 200~208V           | 75   | 100  | 125  |
|                   | 220~240V           | 100  | 125  | 150  |
|                   | 440~480V           | 200  | 250  | 300  |
|                   | 550~600V           | 200  | 250  | 300  |

### Overload Relays

(Class 10A,  
Differential Typical)



MT-400

#### Setting Ranges (A)

|          |
|----------|
| 85-125A  |
| 100-160A |
| 120-185A |
| 160-240A |
| 200-330A |
| 260-400A |

#### Frame Size 400AF

|               |
|---------------|
| MT-400/3K-125 |
| MT-400/3K-160 |
| MT-400/3K-185 |
| MT-400/3K-240 |
| MT-400/3K-330 |
| MT-400/3K-400 |

### Lug Terminals



#### Part. No.

|        |
|--------|
| AJ-220 |
| AJ-400 |
| AJ-800 |

#### Frame Size

|       |
|-------|
| 225AF |
| 400AF |
| 800AF |

Drawings and other technical information can be found on page 14-20.