



Main

Product or component type	Controllers separate parts
Accessory / separate part category	Control accessory
Product specific application	Heavy hoisting applications
Product compatibility	XKM
Accessory / separate part type	Contact block
Number of contacts	4
Contact blow-out type	Magnetic

Complementary

Electrical connection	Screw clamp terminal, connection capacity: 1 x 1.5...2 x 2.5 mm ²
Contact operation	Double-break Slow-break
[Ith] conventional free air thermal current	20 A conforming to IEC 337-1 20 A conforming to NF C 63-140 20 A conforming to VDE 0660
[Ui] rated insulation voltage	500 V AC/DC conforming to IEC 158-1 500 V AC/DC conforming to NF C 20-040 500 V AC/DC conforming to VDE 0110 600 V conforming to CSA C22.2 No 14
Positive opening	With
Resistance across terminals	<= 25 MOhm at 1 A conforming to NF C 93-050
Short-circuit protection	20 A cartridge fuse type gG conforming to IEC 337-1B 20 A cartridge fuse type gG conforming to VDE 0660 part 2
Electrical durability	3000000 cycles DC inductive load at 120 V, power broken = 100 conforming to IEC 337-1 DC-11, operating rate = 60 cyc/mn 0.5 3000000 cycles DC inductive load at 24 V, power broken = 90 conforming to IEC 337-1 DC-11, operating rate = 60 cyc/mn 0.5 3000000 cycles DC inductive load at 48 V, power broken = 100 conforming to IEC 337-1 DC-11, operating rate = 60 cyc/mn 0.5
Product weight	0.74 lb(US) (0.335 kg)

Environment

standards	CENELEC EN 50013
-----------	------------------

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.