

Main

Range	Spacial
Product or component type	Drive flush mounting kit
Accessory / separate part category	Mounting and fixing accessory
Product specific application	Process and utilities
Range compatibility	Spacial SF and SM enclosures: H:>=600 mm x W:>=300 mm Spacial S3D enclosure: H:>=600 mm x W:>=300 mm Altivar variable speed drive ATV630 Altivar variable speed drive ATV930
NEMA size	3
Motor power kW	7.5 kW 220/240 V 11 kW 220/240 V 15 kW 380/480 V 18.5 kW 380/480 V 22 kW 380/480 V
Mounting location	Mode 2 : inside enclosure Mode 1 : back of enclosure on mounting plate
Kit composition	1 x mounting plate with flanges and integrated gasket, steel with anti-corrosive coating. Fixing by screws and nuts 1 x fixing accessories 1 x drilling template 1 x instruction sheet 1 x edge protector profile, plastic.

Complementary

Permanent permissible load	14.3 kg
Colour	Grey RAL 7035
Height	External : 555 mm Cut-out : 503 mm
Width	External : 295 mm Cut-out : 250 mm
Depth	Wall-enclosure separation : 22 mm
Product weight	4.63 lb(US) (2.1 kg)
Services	Configuration of enclosure pre-drilled back at requested dimensions Factory installation drive flush mounting kit on enclosure

Environment

IP degree of protection	IP55 conforming to IEC 60529
-------------------------	------------------------------

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0810 - Schneider Electric declaration of conformity	Compliant - since 0810 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.