

Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

Complementary

System Voltage	240 V AC at 50/60 Hz
[Ie] rated operational current AC	40 A AC-3 60 A AC-1
Motor power hp	5 hp at 240 V AC for 1 phase motors 10 hp at 208 V AC for 3 phases motors 10 hp at 230 V AC for 3 phases motors 3 hp at 120 V AC for 1 phase motors 30 hp at 460 V AC for 3 phases motors 30 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Location of connection	Line
Height	13.98 in (355 mm)
Depth	7.4 in (188 mm)
Width	10.63 in (270 mm)

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 painted sheet steel

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1504 - Schneider Electric declaration of conformity	Compliant - since 1504 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------