



Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing
Disconnecter device type	Fusible disconnect

Complementary

System Voltage	120 V AC at 50/60 Hz
[Ie] rated operational current AC	25 A
Motor power hp	2 hp at 120 V AC for 1 phase motors 3 hp at 240 V AC for 1 phase motors 7.5 hp at 208 V AC for 3 phases motors 7.5 hp at 230 V AC for 3 phases motors 15 hp at 460 V AC for 3 phases motors 20 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Protection type	60 A switch-disconnector fuse
Location of connection	Line

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0801 - Schneider Electric declaration of conformity	Compliant - since 0801 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------