



### Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing
Disconnecter device type	Fusible disconnect

### Complementary

System Voltage	120 V AC at 50/60 Hz
[Ie] rated operational current AC	25 A
Motor power hp	2 hp at 120 V AC for 1 phase motors 3 hp at 240 V AC for 1 phase motors 7.5 hp at 208 V AC for 3 phases motors 7.5 hp at 230 V AC for 3 phases motors 15 hp at 460 V AC for 3 phases motors 20 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Protection type	60 A switch-disconnector fuse
Location of connection	Line

### Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0801 - Schneider Electric declaration of conformity	Compliant - since 0801 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

### Contractual warranty

Warranty period	18 months
-----------------	-----------