

## Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

## Complementary

System Voltage	240 V AC at 50/60 Hz
[Ie] rated operational current AC	80 A AC-1 50 A AC-3
Motor power hp	3 hp at 120 V AC for 1 phase motors 7.5 hp at 240 V AC for 1 phase motors 15 hp at 208 V AC for 3 phases motors 15 hp at 230 V AC for 3 phases motors 40 hp at 460 V AC for 3 phases motors 40 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Location of connection	Line
Height	13.98 in (355 mm)
Depth	7.4 in (188 mm)
Width	10.63 in (270 mm)

## Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 painted sheet steel

## Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1440 - Schneider Electric declaration of conformity	Compliant - since 1440 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

## Contractual warranty

Warranty period	18 months
-----------------	-----------