



Main

Product or component type	Communication card
Range compatibility	Altivar 61 Altivar 71
Communication port protocol	Profinet MRP (Media Redundancy Protocol)
Connector type	2 RJ45 connectors
Transmission rate	100 Mbits
Physical interface	RJ45 Profinet
Web services	Data editor Drive monitor Drive parameters Drive recorder Ethernet/IP setup Ethernet statistics FDR Agent Security IPar client settings Save/restore drive configuration Multi-language services

Complementary

Exchange mode	Full duplex
Communication data link	LLC : IEEE 802.2 MAC : IEEE 802.3
Communication network type	Ethernet CiA 402 profile conforming to IEC 61800-7-201 Ethernet PROFIdrive profile
Communication transport type	TCP CiA 402 profile conforming to IEC 61800-7-201 UDP PROFIdrive profile RT (real-time)
Web server	Embedded
Communication service	FTP IPar-server
Display type	1 LED Link (Link Status) 1 LED MS (Module Status) 1 LED NS (Network Status) 1 LED TX/RX (Transmit/Receive port 1) 1 LED TX/RX (Transmit/Receive port 2)
Product weight	0.63 lb(US) (0.287 kg)

Environment

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1312 - Schneider Electric declaration of conformity	Compliant - since 1312 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.	Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.