

## 2000W 230V AVR Line Conditioner, Power Conditioner, AC Surge Protector, 6 Outlets, Uniplug adapter

MODEL NUMBER: LR2000



### Description

Tripp Lite's LR2000 Automatic Voltage Regulation/AVR power conditioner prevents equipment damage, performance problems and system degradation due to voltage fluctuations, line noise and transient surges. Ensures 230V +/-10% output voltage for computer equipment, home theater systems and other sensitive electronic devices during brownouts to 175 and overvoltages to 253V. Reliable transformer-based voltage regulation offers two available levels of voltage boost to correct severe undervoltages, along with a single level of voltage reduction for overvoltages. Network-grade AC surge and EMI/RFI noise suppression removes power contaminants known to cause system interference, lockups and power-related audio and video artifacts. Extends the useful life of connected equipment by enhancing power supply efficiency and preventing overtemperature conditions. Front panel LEDs offer metered verification of input voltage level in 3 stages. Detachable IEC-320 C14 connector accepts a variety of worldwide replacement cordsets. Includes 6 outlets (2 NEMA 5-15R, 2 NEMA 6-15R and 2 IEC-320 C13), plus one UNIPLUG adapter capable of accommodating dozens of international plug types.

### Features

- Maintains regulated 208/220/240V nominal output (selectable).
- Three levels of voltage stabilization offer targeted response to overvoltages, undervoltages and severe brownouts
- Input voltages over 255V (@240V)/234V (@220V)/221V (@208V) are reduced by 9.8%
- Input voltages between 204-223V (@240V)/ 189-204V (@220V)/ 179-193V (@208V) are boosted by 9%
- Input voltages at or below 205V (@240V)/ 188V (@220V)/ 178 (208V)are boosted by 18.2%
- 2000 watts output power rating supports up to 8.7 amps
- Network grade AC surge suppression
- EMI/RFI noise filtering
- 5 diagnostic LEDs indicate boost, trim and normal AVR operation
- 6 protected outlets (2 NEMA 5-15R/2 NEMA 6-15R/2 IEC-320 C13)
- IEC-320 C14 inlet connection supports user supplied country specific equipment cord set

### Highlights

- Automatic Voltage Regulation - AVR System maintains 230V +/-10%
- Corrects brownouts to 175V and overvoltages to 281V
- Reliable single-cut, dual-boost transformer based voltage correction
- 6 Outlets (2 5-15R, 2 6-15R & 2 C13), 1 UNIPLUG adapter
- 2000 watts

### Applications

- Ideal for use with computer accessories, laser printers, home theater and professional A/V systems, POS equipment and other sensitive electronic devices

### Package Includes

- LR2000 Line Conditioner
- 2m C13 to NEMA 6-15P cord set
- One UNIPLUG international plug adapter
- Instruction manual and warranty information



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

## Specifications

OUTPUT	
Nominal Output Voltage(s) Supported	230V
Output Receptacles	(2) 5-15R; (2) C13; (2) 6-15R
Output (Watts)	2000
Outlet Details	Includes 1 uniplug adapter that converts one of the built-in outlets to accept a variety of country specific plug types
INPUT	
Maximum Input Amps / Watts	10A
Input Cord Length (ft.)	6.5
Input Cord Length (m)	2
USER INTERFACE, ALERTS & CONTROLS	
Front Panel LEDs	5 LEDs show incoming voltage status (Very Low / Low / Normal / High / Very High)
SURGE / NOISE SUPPRESSION	
UPS AC Suppression Joule Rating	1200
EMI / RFI AC Noise Suppression	75 dB
PHYSICAL	
Shipping Weight (lbs.)	8.8
Shipping Weight (kg)	4
Unit Dimensions (hwd / in.)	7 x 6 x 7
Unit Dimensions (hwd / cm)	17.8 x 15.2 x 17.8
Material of Construction	Polycarbonate
Form Factors Supported	Small tower placement supported
WARRANTY	
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	2-year limited warranty
Product Warranty Period (Puerto Rico)	2-year limited warranty



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

Specifications are subject to change without notice. Photos may differ slightly from final products.