



Main

Range	TeSys
Product or component type	Contacteur coil
Range compatibility	TeSys CV1BG contactor TeSys CV3BG contactor TeSys CV3BJ contactor TeSys CV1BH contactor TeSys CV3BH contactor TeSys CV3BK contactor
Control circuit type	AC
Coil type	Low consumption
[Uc] control circuit voltage	110 V AC 50 Hz

Complementary

Control circuit voltage limits	0.85...1.1 Uc at 131 °F (55 °C) operational 50 Hz
Average resistance	4.84 Ohm at 20 °C
Inductance of closed circuit	0.44 H
Inrush power in VA	500...615 VA at 20 °C (cos f 0.31) 50 Hz
Inrush power in W	155...190 W at 20 °C
Hold-in power consumption in VA	60...85 VA at 20 °C (cos f 0.38) 50 Hz
Hold-in power consumption in W	22...35 W at 20 °C
Product weight	0.62 lb(US) (0.28 kg)

Environment

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0801 - Schneider Electric declaration of conformity	Compliant - since 0801 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.