

Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

Complementary

System Voltage	120 V AC at 50/60 Hz
[Ie] rated operational current AC	50 A
Motor power hp	2 hp at 120 V AC for1 phase motors 5 hp at 240 V AC for1 phase motors 10 hp at 208 V AC for3 phases motors 10 hp at 230 V AC for3 phases motors 20 hp at 460 V AC for3 phases motors 25 hp at 575 V AC for3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Protection type	Switch-disconnector fuse
Location of connection	Line

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0801 - Schneider Electric declaration of conformity	Compliant - since 0801 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov