



SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD	CONSTANT IMPEDANCE LOAD	FOR INCREASING VOLTAGE AS VIEWED FROM BASE END		INPUT	JUMPER	OUTPUT	
SINGLE PHASE	120	60	0-120	MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA	CW	1-4	4-3	
				12	1.44	15	1.80	CCW	1-4	1-3	
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±			UNITS			TITLE: SPEC. CONTROL DRAWING					
DECIMALS			IN [mm]			SPEC. CONTROL DRAWING					
.XX			1"			MODEL: 1210B					
.XXX			1-1/2"								
MATERIAL:			ALL DIMENSIONS APPLY AFTER PLATING			DRAWN BY: S.A. SMITH		DATE: 9/24/97		FIRST USED ON: DO NOT SCALE DWG.	
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.			CHECKER:			DATE:		WEIGHT APPROX. 10 LBS		CAGE CODE 83008	
			ENGINEER:			DATE:		SCALE 1=1		SHEET 1 OF 1	
								DWG. NO. 031-2960			