



SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA		INPUT	JUMPER	OUTPUT
SINGLE PHASE	120	60	0-120	12	1.44	15	1.80	CW	1-4	---	4-3
								CCW	1-4	---	1-3
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±			UNITS			TITLE: SPEC. CONTROL DRAWING					
DECIMALS			IN [mm]			SPEC. CONTROL DRAWING					
.XX			Holes .002			SPEC. CONTROL DRAWING					
.XXX			ANGLES 1°			SPEC. CONTROL DRAWING					
.005			DRAFT 1-1/2°			SPEC. CONTROL DRAWING					
MATERIAL:			ALL DIMENSIONS APPLY AFTER PLATING			MODEL: 1210B					
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.			DRAWN BY		DATE	FIRST USED ON	DO NOT SCALE DWG.				
			S.A. SMITH		9/24/97			<b>STACO ENERGY PRODUCTS CO.</b> <small>A Components Corporation of Ameresco Company            302 Gadsden Boulevard Dayton, Ohio 45403 USA</small>			
			CHECKER		DATE	WEIGHT APPROX.	CAGE CODE	DWG. NO. 031-2960			
			ENGINEER		DATE	10 LBS	83008	SCALE 1=1 SHEET 1 OF 1			