

T-1 (3mm) SOLID STATE LAMP

Part Number: WP710A10SYC Super Bright Yellow


Features

- Low power consumption.
- Popular T-1 diameter package.
- General purpose leads.
- Reliable and rugged.
- Long life solid state reliability.
- Available on tape and reel.
- RoHS compliant.

Description

The Super Bright Yellow device is made with AlGaInP (on GaAs substrate) light emitting diode chip.

Package Dimensions







- 1. All dimensions are in millimeters (inches).
- 2. Tolerance is $\pm 0.25(0.01")$ unless otherwise noted.
- 3. Lead spacing is measured where the leads emerge from the package.
 4. The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.

SPEC NO: DSAL0557 **REV NO: V.2** DATE: MAR/07/2011 PAGE: 1 OF 6 CHECKED: Allen Liu APPROVED: WYNEC DRAWN: J.Yu ERP: 1101029223

Selection Guide

Part No.	Dice	Lens Type	lv (mcd) [2] @ 20mA		Viewing Angle [1]
			Min.	Тур.	201/2
WP710A10SYC	Super Bright Yellow (AlGalnP)	WATER CLEAR	900	1500	34°

- 1. 01/2 is the angle from optical centerline where the luminous intensity is 1/2 of the optical peak value. 2. Luminous intensity/ luminous Flux: +/-15%.

Electrical / Optical Characteristics at TA=25°C

Symbol	Parameter	Device	Тур.	Max.	Units	Test Conditions	
λpeak	Peak Wavelength	Super Bright Yellow	590		nm	IF=20mA	
λD [1]	Dominant Wavelength	Super Bright Yellow	590		nm	IF=20mA	
Δλ1/2	Spectral Line Half-width	Super Bright Yellow	28		nm	IF=20mA	
С	Capacitance	Super Bright Yellow	25		pF	VF=0V;f=1MHz	
VF [2]	Forward Voltage	Super Bright Yellow	2	2.5	V	IF=20mA	
IR	Reverse Current	Super Bright Yellow		10	uA	VR = 5V	

- 1.Wavelength: +/-1nm.
- 2. Forward Voltage: +/-0.1V.


Absolute Maximum Ratings at TA=25°C

Parameter	Super Bright Yellow	Units	
Power dissipation	75	mW	
DC Forward Current	30	mA	
Peak Forward Current [1]	150	mA	
Reverse Voltage	5	V	
Operating/Storage Temperature	-40°C To +85°C		
Lead Solder Temperature [2]	260°C For 3 Seconds		
Lead Solder Temperature [3]	260°C For 5 Seconds		


Notes:


- 1. 1/10 Duty Cycle, 0.1ms Pulse Width. 2. 2mm below package base. 3. 5mm below package base.


SPEC NO: DSAL0557 REV NO: V.2 DATE: MAR/07/2011 PAGE: 2 OF 6 APPROVED: WYNEC **CHECKED: Allen Liu** DRAWN: J.Yu ERP: 1101029223




Super Bright Yellow WP710A10SYC











PAGE: 3 OF 6

ERP: 1101029223



SPEC NO: DSAL0557 **REV NO: V.2** DATE: MAR/07/2011 APPROVED: WYNEC **CHECKED: Allen Liu** DRAWN: J.Yu






SPEC NO: DSAL0557 APPROVED: WYNEC REV NO: V.2 CHECKED: Allen Liu DATE: MAR/07/2011 DRAWN: J.Yu PAGE: 4 OF 6 ERP: 1101029223


PRECAUTIONS

1. The lead pitch of the LED must match the pitch of the mounting holes on the PCB during component placement. Lead—forming may be required to insure the lead pitch matches the hole pitch. Refer to the figure below for proper lead forming procedures. (Fig. 1)



" \bigcirc " Correct mounting method "imes" Incorrect mounting method


- 2. When soldering wire to the LED, use individual heat—shrink tubing to insulate the exposed leads to prevent accidental contact short—circuit. (Fig.2)
- 3.Use stand—offs (Fig.3) or spacers (Fig.4) to securely position the LED above the PCB.




- 4. Maintain a minimum of 2mm clearance between the base of the LED lens and the first lead bend. (Fig. 5 and 6)
- 5. During lead forming, use tools or jigs to hold the leads securely so that the bending force will not be transmitted to the LED lens and its internal structures. Do not perform lead forming once the component has been mounted onto the PCB. (Fig. 7)

SPEC NO: DSAL0557 APPROVED: WYNEC REV NO: V.2 CHECKED: Allen Liu DATE: MAR/07/2011 DRAWN: J.Yu PAGE: 5 OF 6 ERP: 1101029223


6. Do not bend the leads more than twice. (Fig. 8)



7. During soldering, component covers and holders should leave clearance to avoid placing damaging stress on the LED during soldering.



- 8. The tip of the soldering iron should never touch the lens epoxy.
- 9. Through—hole LEDs are incompatible with reflow soldering.
- 10. If the LED will undergo multiple soldering passes or face other processes where the part may be subjected to intense heat, please check with Kingbright for compatibility.
- 11. Recommended Wave Soldering Profile for Kingbright Thru-Hole Products



NOTES:

- 1.Recommend the wave temperature 245°C \sim 260°C.The maximum soldering temperature should be less than 260°C.
- 2.Do not apply stress on epoxy resins when temperature is over 85°C.
- 3. The soldering profile apply to the lead free soldering (Sn/Cu/Ag alloy).
- 4.During wave soldering, the PCB top-surface temperature should be kept below 105°C.
- 5.No more than once.

SPEC NO: DSAL0557 REV NO: V.2 DATE: MAR/07/2011 PAGE: 6 OF 6
APPROVED: WYNEC CHECKED: Allen Liu DRAWN: J.Yu ERP: 1101029223