



MAXIMUM OUTPUT CURRENT IN OUTPUT VOLTAGE RANGE FROM 0 TO 25% ABOVE LINE VOLTAGE. AT HIGHER OUTPUT VOLTAGES, THE OUTPUT CURRENT MUST BE REDUCED ACCORDING TO THE DERATING CURVE FIGURE A.

§ MAXIMUM KVA AT MAXIMUM OUTPUT VOLTAGE AND CORRESPONDING DERATED OUTPUT CURRENT. MAXIMUM KVA FOR LOWER VOLTAGES MAY BE CALCULATED FROM DERATING CURVE FIGURE A.

SPECIFICATIONS										
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS		
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD	CONSTANT IMPEDANCE LOAD	FOR INCREASING VOLTAGE AS VIEWED FROM BASE END		INPUT	JUMPER	OUTPUT
SINGLE PHASE	240	50/60	0-240	3.5	0.84	5.0	1.20	CW	1-4	4-3
			0-280	3.5	0.98	—	—	CCW	1-4	1-3
	120	50/60	0-280	3.5#	0.42§	—	—	CW	4-5	4-3
			0-280	3.5#	0.42§	—	—	CCW	1-2	1-3

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±		DECIMALS		HOLES		ANGLES		DRAFT		UNITS		TITLE: SPEC. CONTROL DRAWING	
.XX		.002		1°		1-1/2°		1-1/2°		IN [mm]		DRAWN BY S.A. SMITH	
MATERIAL:		ALL DIMENSIONS APPLY AFTER PLATING		DATE 9/23/97		FIRST USED ON		DO NOT SCALE DWG.		WEIGHT APPROX. 10.25 LBS		CAGE CODE 83008	
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.		CHECKER		DATE		SCALE 1=1		SHEET 1 OF 1		DWG. NO. 031-2355		D	

