



Main

Range	TeSys
Product or component type	Coil
Range compatibility	TeSys Integral contactor breaker
Device short name	LX1
Control circuit type	AC 60 Hz
[Uc] control circuit voltage	230...240 V AC 60 Hz
Average resistance	23.24 Ohm at 68 °F (20 °C)
Inductance of closed circuit	4.5 H

Complementary

Control circuit voltage limits	0.85...1.1 Uc at <= 131 °F (55 °C) operational 0.25...0.7 Uc at <= 131 °F (55 °C) drop-out
Inrush power in VA	420...500 VA (cos φ 0.55) 60 Hz
Hold-in power consumption in VA	24...36 VA (cos φ 0.28) 60 Hz

Environment

product weight	0.66 lb(US) (0.3 kg)
----------------	----------------------

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0808 - Schneider Electric declaration of conformity	Compliant - since 0808 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.