



Main

Range of product	Harmony XAR
Accessory / separate part type	Battery charger
Accessory / separate part category	Electrical accessory

Complementary

[Us] rated supply voltage	100...240 V AC
Network frequency	50...60 Hz
Nominal output current	0.9 Aat 90 V AC
Connections - terminals	5-position plug-in connector
Product weight	0.57 lb(US) (0.26 kg)

Environment

ambient air temperature for operation	> 32...104 °F (> 0...40 °C)
ambient air temperature for storage	> -4...140 °F (> -20...60 °C)

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1415 - Schneider Electric declaration of conformity	Compliant - since 1415 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Nickel compounds, which is known to the State of California to cause cancer, and	Nickel compounds, which is known to the State of California to cause cancer, and
Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.