



Main

Device short name	KY
Enclosure type	Weatherproof enclosure dust and oil resistant indoor/outdoor
Mounting diameter	1.18 in (30 mm)
Provided equipment	Legend plate 1 KN202 Contact block 3 KA1 Legend plate 1 KN210 Legend plate 1 KN211

Complementary

Line Rated Current	10 A
Contacts type and composition	3 NO + 3 NC
Control type	Push-button 1 9001KR3R Push-button 2 9001KR1B
Device mounting	Surface
Electrical connection	Screw clamp terminal
Enclosure material	Die cast zinc alloy grey
Marking	UP-DOWN-STOP
Operator profile	3 projecting push-buttons
Permissible voltage	<= 300 V

Environment

NEMA degree of protection	NEMA 3/4/13
product certifications	CE CSA LR25490 class 3211 03 UL listed file E42259 CCN NKCR

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1002 - Schneider Electric declaration of conformity	Compliant - since 1002 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Nickel compounds, which is known to the State of California to cause cancer, and	Nickel compounds, which is known to the State of California to cause cancer, and
Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.