



| JKL LAMP NUMBER | VOLTS RATED | WATTS | INITIAL MSCP | INITIAL LUMENS | AVERAGE LIFE HRS. | FILAMENT TYPE |
|-----------------|-------------|-------|--------------|----------------|-------------------|---------------|
| 6S6-12V | 12 | 6 | 3.58 | 45.0 | 1,500 | C-2V |
| 6S6-30V | 30 | 6 | 3.98 | 50.0 | 1,500 | C-2V |
| 6S6-120V | 120 | 6 | 3.18 | 40.0 | 1,500 | C-7A |
| 6S6-145V | 145 | 6 | 3.18 | 40.0 | 1,500 | C-7A |
| 6S6-155V | 155 | 6 | 3.18 | 40.0 | 1,500 | C-7A |
| 10S6-230V | 230 | 10 | 5.97 | 75.0 | 1,500 | C-1 |
| 10S6-250V | 250 | 10 | 5.97 | 75.0 | 1,500 | C-1 |

| | | | | | | | |
|--|------------------------|---|----------|-----------------------------------|---------------|---------------------------|--|
| METRIC  THIRD ANGLE PROJECTION | | DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0 | | JKL COMPONENTS CORPORATION | | | |
| DRAWN BY | | APPVD BY DATE | | SIZE | FSCM NO. | DRAWING NO. | |
| L. WENGSTROM | | Q.C. 3/1/01 | | A | 55335 | SCREW BASE CANDELABRA S-6 | |
| - CAD DRAWING - | | | | SCALE | RELEASED DATE | REVISION DATE | |
| MANUAL REVISIONS NOT PERMITTED | | | | NONE | 3/1/01 | | |
| REV. NO. | DESCRIPTION/ECO NUMBER | APPVD DATE | REV. NO. | SHEET | 1 OF 1 | | |