



Main

| | |
|-----------------------------|---|
| Product or component type | Communication card |
| Range compatibility | Altivar 61 Altivar 71 |
| Communication port protocol | Ethernet/IP Modbus TCP |
| Connector type | 2 RJ45 connectors |
| Transmission rate | 10/100 Mbps |
| Physical interface | IEEE 802.3 Ethernet IP/Modbus TCP |
| Web services | Altivar chart Altivar viewer Data editor Drive monitor Drive parameters Drive recorder E-mail Ethernet/IP scanner setup Ethernet/IP setup Ethernet statistics FDR Agent Message statistics Security Modbus TCP scanner setup |

Complementary

| | |
|------------------------------|--|
| Exchange mode | Half duplex and full duplex |
| Communication data link | LLC : IEEE 802.2 MAC : IEEE 802.3 |
| Communication network type | ICMP IP conforming to RFC791 |
| Communication transport type | TCP conforming to RFC793 UDP |
| Web server | Embedded |
| Communication service | CiA 402 profile CIP AC Drive (02) profile Diagnostics (08) FTP I/O profile Read holding registers (03) Read input registers (04) Read/write multiple registers (23) SNMP TFTP Write multiple registers (16) Write single register (06) Read device identification (43/14) Ethernet/IP adapter |
| Display type | 1 LED Link (Link Status) 1 LED MS (Module Status) 1 LED NS (Network Status) 1 LED TX/RX (Transmit/Receive port 1) 1 LED TX/RX (Transmit/Receive port 2) Graphic display terminal control word received Graphic display terminal number of frames received Graphic display terminal reference received |
| Product weight | 0.66 lb(US) (0.3 kg) |

Environment

Offer Sustainability

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Not Green Premium product

Not Green Premium product

Compliant - since 1315 - Schneider Electric declaration of conformity

Compliant - since 1315 - Schneider Electric declaration of conformity

WARNING: This product can expose you to chemicals including:

WARNING: This product can expose you to chemicals including:

Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.

Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.

Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.

Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.

For more information go to www.p65warnings.ca.gov

For more information go to www.p65warnings.ca.gov