


20-Bit, 2-Port Bus Switch

Features

- Near-Zero propagation delay
- 5Ω or 25Ω switches connect inputs to outputs
- · Direct bus connection when switches are ON
- 32X384 function with flow through pinout make board layout easier
- Ultra-low quiescent power (0.2µA typical)
 - Ideally suited for notebook applications
- Industrial operating temperature: -40°C to +85°C
- Packaging (Pb-free & Green):
 48-pin 240-mil wide plastic TSSOP (A)

Block Diagram



Truth Table⁽¹⁾

Function	BEx	A19-A0
Disconnect	Н	Hi-Z
Connect	L	B19-B0

Note:

1. H = High Voltage Level, L = Low Voltage Level, Hi-Z = High Impedance

Description

Pericom Semiconductor's PI5C16861 is configured as a 20-bit, 2-port bus switch designed with a low On-Resistance (5Ω) allowing inputs to be connected directly to outputs. The bus switch creates no additional propagational delay or additional ground bounce noise. The switches are turned ON by the Bus Enable (\overline{BEx}) input signal.

Pin Configuration

NC E	1 ()	48 🛛 VCC
A0 🛙	2	47 🛛 🗚
A1 [3	46 🛛 во
A2 🛙	4	45 🛛 B1
АЗ 🛙	5	44 🛛 B2
A4 🛙	6	43 🛛 ВЗ
A5 🛙	7	42 🛛 B4
A6 🛛	8	41 🛛 B5
A7 🛛	9	40 🛛 В6
A8 🛛	10	39 🛛 В7
A9 🛛	11	38 🛛 В8
GND [12	37 🛛 В9
NC [13	36 🛛 VCC
A10 🛛	14	35 🛛 BE2
A11 [15	34 🛛 B10
A12 🛛	16	33 🛛 B11
A13 [17	32 🛛 B12
A14 🛛	18	31 🛛 B13
A15 🛛	19	30 🛛 B14
A16 🛛	20	29 🛛 B15
A17 🛛	21	28 🛛 B16
A18 [22	27 🛛 B17
A19 🛛	23	26 🛛 B18
GND [24	25 🛛 B19

Pin Description

Pin Name	Description	
BEx	Bus Enable Inputs (Active LOW)	
A19-A0	Bus A	
B19-B0	Bus B	

Maximum Ratings

(Above which the useful life may be impaired. For user guidelines, not tested.)

	-
Storage Temperature	Note:
Ambient Temperature with Power Applied40°C to +85°C	Stresse INGS 1
Supply Voltage to Ground Potential (Inputs & V _{CC} Only)0.5V to +7.0V	a stress
Supply Voltage to Ground Potential (Outputs & D/O Only)0.5V to +7.0V	at thes the ope
DC Input Voltage0.5V to +7.0V	Exposi
DC Output Current	tended
Power Dissipation	

Stresses greater than those listed under MAXIMUM RAT-INGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

Parameters	Description	Test Conditions ⁽¹⁾	Min.	Typ. ⁽²⁾	Max.	Units	
V _{IH}	Input HIGH Voltage	Guaranteed Logic HIGH Level	2.0			v	
V _{IL}	Input LOW Voltage	Guaranteed Logic LOW Level	-0.5		0.8		
I _{IH}	Input HIGH Current	$V_{CC} = Max., V_{IN} = V_{CC}$			±1		
I _{IL}	Input LOW Current	$V_{CC} = Max., V_{IN} = GND$			±1	μA	
I _{OZH}	High Impedance Output Current	$0 \le A, B \le V_{CC}$			±1	μΑ	
V _{IK}	Clamp Diode Voltage	$V_{CC} = Min., I_{IN} = -18mA$		-0.7	-1.2	V	
ION	Short Circuit Current ⁽³⁾	$A(B) = 0V, B(A) = V_{CC}$	100			mA	
V_{H}	Input Hysteresis at Con- trol Pins			150		mV	
D	Switch On-Resistance ⁽⁴⁾	$V_{CC} = Min., V_{IN} = 0.0V$		5	7	Ω	
R _{ON}		$V_{CC} = Min., V_{IN} = 2.4V$		10	15		

Notes:

- 1. For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.
- 2. Typical values are at $V_{CC} = 5.0V$, $T_A = 25^{\circ}C$ ambient and maximum loading.
- 3. Not more than one output should be shorted at one time. Duration of the test should not exceed one second.
- 4. Measured by the voltage drop between A and B pin at indicated current through the switch. On-Resistance is determined by the lower of the voltages on the two (A,B) pins.

Capacitance ($T_A = 25^{\circ}C$, f = 1 MHz)

Parameters ⁽¹⁾	Description	Test Conditions	Тур.	Units
C _{IN}	Input Capacitance		6	
C _{OFF}	A/B Capacitance, Switch Off	$V_{IN} = 0V$	6	pF
C _{ON}	A/B Capacitance, Switch On		8	

Notes:

1. This parameter is determined by device characterization but is not production tested.



Power Supply Characteristics

Parameters	Description	Test Conditions ⁽¹⁾		Min.	Typ. ⁽²⁾	Max.	Units
I _{CC}	Quiescent Power Supply Current	$V_{CC} = Max.$	$V_{IN} = GND$ or V_{CC}		0.1	10	μA
ΔI _{CC}	Supply Current per Input @ TTL HIGH	$V_{CC} = Max.$	$V_{IN} = 3.4 V^{(3)}$			2.5	mA
I _{CCD}	Supply Current per Input per MHz ⁽⁴⁾	V _{CC} = Max., A and B Pins Open BEx = GND, Control Input Toggling 50% Duty Cycle				0.25	mA/ MHz

Notes:

1. For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device.

2. Typical values are at $V_{CC} = 5.0V$, $+25^{\circ}C$ ambient.

3. Per TTL driven input (V_{IN} = 3.4V, control inputs only); A and B pins do not contribute to I_{CC}.

4. This current applies to the control inputs only and represent the current required to switch internal capacitance at the specified frequency. The A and B inputs generate no significant AC or DC currents as they transition. This parameter is not tested, but is guaranteed by design.

PI5C16861 Switching Characteristics over Operating Range

			PI5C	16861	
Parameters	Description	Conditions	Ca	m.	Unit
			Min.	Max.	
t _{PLH} t _{PHL}	Propagation Delay ^(1,2) Ax to Bx, Bx to Ax			1.25	
t _{PZH} t _{PZL}	Bus Enable Time BEx to Ax or Bx	$C_{L} = 50 pF$ $R_{L} = 500 \Omega$	1.5	6.5	ns
t _{PHZ} t _{PLZ}	Bus Disable Time BEx to Ax or Bx		1.5	5.5	


Notes:

1. This parameter is guaranteed but not tested on Propagation Delays.

2. The bus switch contributes no propagational delay other than the RC delay of the On-Resistance of the switch and the load capacitance. The time constant for the switch alone is of the order of 0.25ns for 50pF load. Since this time constant is much smaller than the rise/fall times of typical driving signals, it adds very little propagational delay to the system. Propagational delay of the bus switch when used in a system is determined by the driving circuit on the driving side of the switch and its interaction with the load on the driven side.



Packaging Mechanical: 48-pin BSQOP (B)



Ordering Information

Ordering Code	Package Type	Package Description
PI5C16861AE	А	Pb-free & Green, 48-Pin, TSSOP

Notes:

- Thermal characteristics can be found on the company web site at www.pericom.com/packaging/
- E = Pb-free & Green
- Adding an X suffix = Tape/Reel

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Diodes Incorporated: <u>PI5C16861AE</u> <u>PI5C16861AEX</u>