



*Quality Products. Service Excellence.*

## Low Voltage PCB Mount - Low Profile 162-164 Series

### Features



- 20 output voltages to choose from (5 - 120VAC R.M.S.)
- Six VA size models available from - 1.1 to 36VA
- Both series operate on 50/60 Hz current
- Low profile, split bobbin design.
- Dual winding secondaries, non-concentrically wound
- Units are designed so that all windings must be used
- Low primary to secondary coupling - no electrostatic shield required.
- Choice of economical single primary 115V (164 series) or universal dual primary 115/230V (162 series) - either model 50/60 Hz operation.
- High insulation - Hipot of 2,500V RMS.
- Class B insulation - 130 degrees C.
- No mounting hardware required on 1.1 and 2.4 VA sizes, two hole mounting on 6, 12 and 20VA sizes, four hole mounting on 36VA size (mounting screws not provided). P.C. board mount with industry standard pin spacing.
- c UL us recognized



**Single Primary  
164 Series**



**Dual Primary  
162 Series**



| Part No<br>Single Primary<br>115V | Part No<br>Dual Primary<br>115/230V | Size<br>VA | Series             | Secondary (RMS)<br>Parallel |
|-----------------------------------|-------------------------------------|------------|--------------------|-----------------------------|
| 164D10                            | 162D10                              | 1.1        | 10V C.T. @ .11A    | 5V @ .22A                   |
| 164E10                            | 162E10                              | 2.4        | 10V C.T. @ .25A    | 5V @ .5A                    |
| 164F10                            | 162F10                              | 6          | 10V C.T. @ .6A     | 5V @ 1.2A                   |
| 164G10                            | 162G10                              | 12         | 10V C.T. @ 1.2A    | 5V @ 2.4A                   |
| 164H10                            | 162H10                              | 20         | 10V C.T. @ 2A      | 5V @ 4.0A                   |
| 164J10                            | 162J10                              | 36         | 10V C.T. @ 3.6A    | 5V @ 7.2A                   |
| 164D12                            | 162D12                              | 1.1        | 12.6V C.T. @ .09A  | 6.3V @ .18A                 |
| 164E12                            | 162E12                              | 2.4        | 12.6V C.T. @ .2A   | 6.3V @ .4A                  |
| 164F12                            | 162F12                              | 6          | 12.6V C.T. @ .5A   | 6.3V @ 1.0A                 |
| 164G12                            | 162G12                              | 12         | 12.6V C.T. @ 1.0A  | 6.3V @ 2.0A                 |
| 164H12                            | 162H12                              | 20         | 12.6V C.T. @ 1.6A  | 6.3V @ 3.2A                 |
| 164J12                            | 162J12                              | 36         | 12.6V C.T. @ 2.85A | 6.3V @ 5.7A                 |
| 164D16                            | 162D16                              | 1.1        | 16V C.T. @ .07A    | 8V @ .14A                   |
| 164E16                            | 162E16                              | 2.4        | 16V C.T. @ .15A    | 8V @ .3A                    |
| 164F16                            | 162F16                              | 6          | 16V C.T. @ .4A     | 8V @ .8A                    |
| 164G16                            | 162G16                              | 12         | 16V C.T. @ .8A     | 8V @ 1.6A                   |
| 164H16                            | 162H16                              | 20         | 16V C.T. @ 1.25A   | 8V @ 2.5A                   |
| 164J16                            | 162J16                              | 36         | 16V C.T. @ 2.25A   | 8V @ 4.5A                   |
| 164D20                            | 162D20                              | 1.1        | 20V C.T. @ .055A   | 10V @ .11A                  |
| 164E20                            | 162E20                              | 2.4        | 20V C.T. @ .12A    | 10V @ .24A                  |
| 164F20                            | 162F20                              | 6          | 20V C.T. @ .3A     | 10V @ .6A                   |
| 164G20                            | 162G20                              | 12         | 20V C.T. @ .6A     | 10V @ 1.2A                  |
| 164H20                            | 162H20                              | 20         | 20V C.T. @ 1A      | 10V @ 2.0A                  |
| 164J20                            | 162J20                              | 36         | 20V C.T. @ 1.8A    | 10V @ 3.6A                  |
| 164D24                            | 162D24                              | 1.1        | 24V C.T. @ .045A   | 12V @ .09A                  |
| 164E24                            | 162E24                              | 2.4        | 24V C.T. @ .1A     | 12V @ .2A                   |

| Part No<br>Single Primary<br>115V | Part No<br>Dual Primary<br>115/230V | Size<br>VA | Series           | Secondary (RMS)<br>Parallel |
|-----------------------------------|-------------------------------------|------------|------------------|-----------------------------|
| 164F24                            | 162F24                              | 6          | 24V C.T. @ .25A  | 12V @ .5A                   |
| 164G24                            | 162G24                              | 12         | 24V C.T. @ .5A   | 12V @ 1.0A                  |
| 164H24                            | 162H24                              | 20         | 24V C.T. @ .8A   | 12V @ 1.6A                  |
| 164J24                            | 162J24                              | 36         | 24V C.T. @ 1.5A  | 12V @ 3.0A                  |
| 164D28                            | 162D28                              | 1.1        | 28V C.T. @ .04A  | 14V @ .08A                  |
| 164E28                            | 162E28                              | 2.4        | 28V C.T. @ .085A | 14V @ .17A                  |
| 164F28                            | 162F28                              | 6          | 28V C.T. @ .2A   | 14V @ .4A                   |
| 164G28                            | 162G28                              | 12         | 28V C.T. @ .42A  | 14V @ .84A                  |
| 164H28                            | 162H28                              | 20         | 28V C.T. @ .7A   | 14V @ 1.4A                  |
| 164J28                            | 162J28                              | 36         | 28V C.T. @ 1.3A  | 14V @ 2.6A                  |
| 164D36                            | 162D36                              | 1.1        | 36V C.T. @ .03A  | 18V @ .06A                  |
| 164E36                            | 162E36                              | 2.4        | 36V C.T. @ .065A | 18V @ .13A                  |
| 164F36                            | 162F36                              | 6          | 36V C.T. @ .17A  | 18V @ .34A                  |
| 164G36                            | 162G36                              | 12         | 36V C.T. @ .35A  | 18V @ .7A                   |
| 164H36                            | 162H36                              | 20         | 36V C.T. @ .55A  | 18V @ 1.1A                  |
| 164J36                            | 162J36                              | 36         | 36V C.T. @ 1A    | 18V @ 2.0A                  |
| 164D48                            | 162D48                              | 1.1        | 48V C.T. @ .023A | 24V @ .046A                 |
| 164E48                            | 162E48                              | 2.4        | 48V C.T. @ .05A  | 24V @ .1A                   |
| 164F48                            | 162F48                              | 6          | 48V C.T. @ .125A | 24V @ .25A                  |
| 164G48                            | 162G48                              | 12         | 48V C.T. @ .25A  | 24V @ .5A                   |
| 164H48                            | 162H48                              | 20         | 48V C.T. @ .4A   | 24V @ .8A                   |
| 164J48                            | 162J48                              | 36         | 48V C.T. @ .75A  | 24V @ 1.5A                  |
| 164D56                            | 162D56                              | 1.1        | 56V C.T. @ .02A  | 28V @ .04A                  |
| 164E56                            | 162E56                              | 2.4        | 56V C.T. @ .045A | 28V @ .09A                  |
| 164F56                            | 162F56                              | 6          | 56V C.T. @ .11A  | 28V @ .22A                  |
| 164G56                            | 162G56                              | 12         | 56V C.T. @ .22A  | 28V @ .44A                  |
| 164H56                            | 162H56                              | 20         | 56V C.T. @ .35A  | 28V @ .7A                   |
| 164J56                            | 162J56                              | 36         | 56V C.T. @ .65A  | 28V @ 1.3A                  |
| 164D120                           | 162D120                             | 1.1        | 120V C.T. @ .01A | 60V @ .02A                  |
| 164E120                           | 162E120                             | 2.4        | 120V C.T. @ .02A | 60V @ .04A                  |
| 164F120                           | 162F120                             | 6          | 120V C.T. @ .05A | 60V @ .1A                   |
| 164G120                           | 162G120                             | 12         | 120V C.T. @ .1A  | 60V @ .2A                   |
| 164H120                           | 162H120                             | 20         | 120V C.T. @ .16A | 60V @ .32A                  |
| 164J120                           | 162J120                             | 36         | 120V C.T. @ .3A  | 60V @ .6A                   |

## Mechanical & Schematic Data

| (VA)<br>Size | Part Number<br>Letter | Dimensions |      |       |      |      |      |      |      |      |    | Mounting<br>Screw | Weight<br>lbs. |
|--------------|-----------------------|------------|------|-------|------|------|------|------|------|------|----|-------------------|----------------|
|              |                       | L          | W    | H     | A    | B    | C    | M    | N    | P    |    |                   |                |
| 1.1          | D                     | 1.38       | 1.13 | 15/16 | 0.25 | 0.25 | 1.2  | -    | -    | -    | -  | 0.17              |                |
| 2.4          | E                     | 1.38       | 1.13 | 1.19  | 0.25 | 0.25 | 1.2  | -    | -    | -    | -  | 0.25              |                |
| 6            | F                     | 1.63       | 1.31 | 1.31  | 0.25 | 0.35 | 1.28 | 1.06 | -    | -    | #4 | 0.44              |                |
| 12           | G                     | 1.88       | 1.56 | 1.50  | 0.30 | 0.40 | 1.41 | 1.25 | -    | -    | #4 | 0.7               |                |
| 20           | H                     | 2.25       | 1.88 | 1.44  | 0.30 | 0.40 | 1.6  | 1.5  | -    | -    | #4 | 0.8               |                |
| 36           | J                     | 2.63       | 2.19 | 1.56  | 0.40 | 0.40 | 1.85 | -    | 1.75 | 2.19 | #6 | 1.1               |                |

Data subject to change without notice

© 2020. Hammond Manufacturing Ltd. All rights reserved.

