



### Main

Range	TeSys
Device short name	LA1LC
Product or component type	Auxiliary contact

### Complementary

Range compatibility	TeSys Integral LD5LD contactor breaker
Mounting location	Left side
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 NO
[U <sub>i</sub> ] rated insulation voltage	690 V
[I <sub>th</sub> ] conventional free air thermal current	6 A
Connections - terminals	Screw clamp terminals 2 cable 1.5 mm <sup>2</sup> Screw clamp terminals 1 cable 2.5 mm <sup>2</sup>
Product weight	0.22 lb(US) (0.1 kg)

### Environment

environmental characteristic	Standard environment
------------------------------	----------------------

### Offer Sustainability

WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Styrene, which is known to the State of California to cause cancer.	Styrene, which is known to the State of California to cause cancer.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

### Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.