

Fustat Fuse Adapters



Specifications

Description: Adapters for using Type S and SL rejection fuses in Edison base fuse sockets.

Features and Benefits

- Fustat adapters screw into the “Edison” thread fuse sockets of standard fuse boxes making it easy to retrofit existing fuse installations
- Available in various amp ratings to cover a wide range of rating requirements

Typical Applications

- Plug fuse installations where it is desirable to restrict fuse amp ratings

Catalog Numbers (Amps)

SA-1*	SA-3- $\frac{2}{10}$ *	SA-10*
SA-1- $\frac{1}{4}$ *	SA-4*	SA-15**
SA-1- $\frac{6}{10}$ *	SA-5*	SA-20**
SA-2*	SA-6- $\frac{1}{4}$ *	SA-30**
SA-2- $\frac{1}{2}$ *	SA-8*	

* Single motor circuits.

** Branch circuits.

Fustat® Adapters for Small Motor Protection*

Adapter	Accepts Fuses
SA-1	S-1 or smaller
SA-1- $\frac{1}{4}$	S-1- $\frac{1}{4}$ or smaller
SA-1- $\frac{6}{10}$	S-1- $\frac{6}{10}$ or smaller
SA-2	S-2 or S-1- $\frac{9}{10}$
SA-2- $\frac{1}{2}$	S-2- $\frac{1}{2}$ to S-1- $\frac{9}{10}$
SA-3- $\frac{2}{10}$	S-3- $\frac{2}{10}$ to S-1- $\frac{9}{10}$
SA-4	S-4 to S-3- $\frac{1}{2}$
SA-5	S-5 to S-3- $\frac{1}{2}$
SA-6- $\frac{1}{4}$	S-6- $\frac{1}{4}$ to S-3- $\frac{1}{2}$
SA-8	S-8 to S-7
SA-10	S-10 to S-7
SA-15	S-15 to S-7
SA-20	S-20
SA-30	S-30 to S-20

* Both motor running and short-circuit protection.

Fustat® Adapters for Branch Circuit Protection

Adapter	Accepts Fuses
SA-15	S-15 to S-7
SA-20	S-20
SA-30	S-25
SA 30	S-30 to S-20