




DWG. SIZE	DWG. NO.		
D	031-3018		
REVISIONS			
SYM.	E.C.N.	DATE	APVD.
A	24194	4/10/00	
	DELETED BLIND HOLES		
B	25121	5/13/03	
	DELETED OLD LOGO		



(4) STANDOFFS TAPPED
1/4-28 X .38 [9.5] DEEP
FOR MOUNTING BOLTS

.88 [22.2] DIA. KNOCKOUT
(5) PLACES FOR
WIRING CONNECTIONS



SCHEMATIC
THREE PHASE OPEN DELTA AND SINGLE
PHASE SERIES. FUSE RECOMMENDED BUT
NOT SUPPLIED.

- ⌘ IF GANGED UNITS ARE USED IN A SYSTEM THAT ORDINARILY HAS A COMMON NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMER WILL BE DAMAGED.
- JUMPER PROVIDED IN STANDARD COMMON POSITION AND SHOULD BE MOVED OR REMOVED AS REQUIRED.

++ LINE TO LINE VOLTAGE.

SPECIFICATIONS													
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS					
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END ■					
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT		
SINGLE PHASE SERIES	240	60	0-240	12	2.88	15	3.60	CW	1-1	4-4	3-3		
								CCW	4-4	1-1	3-3		
THREE PHASE OPEN DELTA π	120 ++	60	0-120	12	2.49	15	3.12	CW	1-4-1	4-4	3-4-3		
								CCW	4-1-4	1-1	3-1-3		
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT .XX .005 .002 1° 1-1/2° MATERIAL: .003				TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1210BCT-2				 A Components Corporation of America Company 303 Gadsden Boulevard Dayton, Ohio 45403 USA					
ALL DIMENSIONS APPLY AFTER PLATING				DRAWN BY S.A. SMITH DATE 9/25/97 FIRST USED ON DO NOT SCALE DWG. CAGE CODE 83008 DWG. NO. 031-3018									
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.				DRAWN BY S.A. SMITH		DATE 9/25/97		FIRST USED ON		DO NOT SCALE DWG.			
				CHECKER		DATE		WEIGHT APPROX. 22.5 LBS		CAGE CODE 83008		DWG. NO. 031-3018	
				ENGINEER		DATE		SCALE 1 = 1		SHEET 1 OF 1		D	

