



## Main

Range	TeSys
Product or component type	Coil
Range compatibility	TeSys Integral contactor breaker
Device short name	LX1
Control circuit type	AC 50 Hz
[Uc] control circuit voltage	110 V AC 50 Hz
Average resistance	6.48 Ohm at 68 °F (20 °C)
Inductance of closed circuit	1.48 H

## Complementary

Control circuit voltage limits	0.85...1.1 Uc at <= 131 °F (55 °C) operational 0.25...0.7 Uc at <= 131 °F (55 °C) drop-out
Inrush power in VA	350...400 VA (cos φ 0.55) 50 Hz
Hold-in power consumption in VA	20...30 VA (cos φ 0.28) 50 Hz

## Environment

product weight	0.66 lb(US) (0.3 kg)
----------------	----------------------

## Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0808 - Schneider Electric declaration of conformity	Compliant - since 0808 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Available	Available
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

## Contractual warranty

Warranty period	18 months
-----------------	-----------