



Main

Range of product	Linery
Product or component type	Cable end
Cable end size	Long
Standards	NF C 63-023
Type of packing	Bag
Quantity per set	Set of 100
Cable cross section	0.02 in ² (16 mm ²)

Complementary

Cable end type	Single conductor
Additional information	For additional marker tag holder
Color	White
Bezel material	Halogen-free plastic
Tube material	Copper conforming to ISO 1337
Number of cables	1
AWG gauge	AWG 6
Bezel size	Ø 9.6 mm
Tube diameter	6.2 mm
Length	1.1 in (28 mm)
Tube length	18 mm
CAD overall depth	1.1 in (28 mm)
Product weight	0.22 lb(US) (0.1 kg)

Environment

ambient air temperature for operation	-4...221 °F (-20...105 °C)
---------------------------------------	----------------------------

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0437 - Schneider Electric declaration of conformity	Compliant - since 0437 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.