



Main

Product or component type	Replacement battery cartridge
Battery type	Lead-acid battery
Product brand	Schneider Electric

Complementary

Number of batteries	1
Battery capacity	84 Ah
Device mounting	Enclosed battery cartridge
Battery life	3...5 yr
Color	Black
Product weight	5.51 lb(US) (2.5 kg)
Height	4.13 in (105 mm)
Width	5.94 in (151 mm)
Depth	2.56 in (65 mm)

Environment

relative humidity	0...95 % (operating) 0...95 % (storage)
operating altitude	0...9842.52 ft (0...3000 m)
storage altitude	0...49212.6 ft (0...15000 m)
ambient air temperature for operation	32...104 °F (0...40 °C)
ambient air temperature for storage	5...113 °F (-15...45 °C)

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0806 - Schneider Electric declaration of conformity	Compliant - since 0806 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.	Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.